

# SCIENTIFIC AMERICAN

[Entered at the Post Office of New York, N. Y., as Second Class Matter. Copyrighted, 1889, by Munn & Co.]

A WEEKLY JOURNAL OF PRACTICAL INFORMATION, ART, SCIENCE, MECHANICS, CHEMISTRY, AND MANUFACTURES.


Vol. LX.—No. 25.  
ESTABLISHED 1845.

NEW YORK, JUNE 22, 1889.


\$3.00 A YEAR.  
WEEKLY.

## COLLAPSE OF THE SOUTH FORK DAM AND DESTRUCTION OF JOHNSTOWN.

The general features of the fatal disaster at Johnstown, Pa., due to the failure of the South Fork dam, by which, in a couple of hours, so many thousand lives were lost, were given in our last issue. It was due to a very severe storm, which had overtaken the capacity of the dam. We give in this paper a number of illustrations of the localities affected, which will serve to make still clearer the ultimate and proximate causes of the disaster. The South Fork lake is now extinct; the great crevasse in the dam gives passage to an insignificant stream of water that, before reaching it, winds through what was once the bottom of the lake. Well up on the sides of the valley once filled with the waters of the lake are the cottages and club house of the South Fork Hunting and Fishing Club. Before the disaster, Mr. John G. Parke, Jr., a civil engineer, was directing some work upon a drainage system designed to carry the refuse water away from these houses to



VIEW OF THE INTERIOR OF THE DAM AFTER THE ACCIDENT.




BURIED LOCOMOTIVES AND WRECK OF CARS AT EAST CONEMAUGH.

the lower side of the dam, in order to prevent the contamination of the water. He had found the water rapidly rising, and went up toward the upper end of the lake. There he found the woods "boiling full of water," as he expressed it. An attempt was made to strengthen the dam by running a plow along its top and throwing earth in against its face. As the rise continued, a gang of men were set to work, and a cut about twenty feet wide and three feet deep was excavated on the west side, giving a spillway, through which a torrent of water escaped. At the other end of the dam the regular spillway, of considerably greater dimensions, was also discharging water. Still the lake rose, and at 11:30 a. m. Mr. Parke gave up hope of averting an overflow. He galloped down to South Fork, and sent men off to the telegraph office with warnings for Johnstown and the other villages. At about one o'clock he reached the dam again, and walked over it. About three inches of water was upon it, pouring down the outer slope and gradually eating away the face. At three o'clock the break began, a piece ten feet in width near the center first succumbing. In three-quarters of an hour the base of the dam was reached, and the lake was empty.

Two of our views show the dam as it appeared a few days after the accident, viewed from the interior, or lake side. Another view shows the lake as it appeared before the accident, with the spillway crossed by bridges. The dam was an embankment about eight hundred feet long and seventy-five feet high, with practically equal slopes on each side of about forty-five degrees. The top was

(Continued on page 390.)



PRESENT APPEARANCE OF SOUTH FORK DAM.—[From sketches made on the spot by special artist of Sci. Am.]



# Scientific American.

ESTABLISHED 1845.

MUNN &amp; CO., Editors and Proprietors.

PUBLISHED WEEKLY AT

No. 361 BROADWAY, NEW YORK.

O. D. MUNN.

A. E. BEACH.

## TERMS FOR THE SCIENTIFIC AMERICAN.

One copy, one year, for the U. S. or Canada.....\$3 00  
 One copy, six months, for the U. S. or Canada..... 1 50  
 One copy, one year, to any foreign country belonging to Postal Union, 4 00  
 Remit by postal or express money order.

**Australia and New Zealand.**—Those who desire to receive the SCIENTIFIC AMERICAN, for a little over one year, may remit \$1 in current Colonial bank notes. Address  
 MUNN & CO., 361 Broadway, corner of Franklin Street, New York.

## The Scientific American Supplement

is a distinct paper from the SCIENTIFIC AMERICAN. THE SUPPLEMENT is issued weekly. Every number contains 16 octavo pages, uniform in size with SCIENTIFIC AMERICAN. Terms of subscription for SUPPLEMENT, \$5.00 a year, for U. S. and Canada. \$6.00 a year to foreign countries belonging to the Postal Union. Single copies, 10 cents. Sold by all newsdealers throughout the country.

**Combined Rates.**—The SCIENTIFIC AMERICAN and SUPPLEMENT will be sent for one year, to any address in U. S. or Canada, on receipt of seven dollars.

The safest way to remit is by draft, postal order, express money order, or registered letter.

**Australia and New Zealand.**—The SCIENTIFIC AMERICAN and SUPPLEMENT will be sent for a little over one year on receipt of £2 current Colonial bank notes. Address MUNN & CO., 361 Broadway, corner of Franklin Street, New York.

NEW YORK, SATURDAY, JUNE 22, 1889.

## Contents.

(Illustrated articles are marked with an asterisk.)

Acid, sulphuric, safe transporta- tion.....	385	Magnetism, effect of light on.....	389
Advice, not bad.....	387	Mausoleum, new.....	392
Appliances, railway.....	384	Melons, about.....	382
Aspirators for laboratory use.....	387	Metals, new.....	387
Bronze, antiquity of.....	393	Milk, heating.....	388
Business and personal.....	394	Mosquitoes, to expel.....	385
Chest, boiling, McEwen's.....	386	Notes and queries.....	394
Culture, bulb, Holland.....	392	Notes, photographic.....	392
Dam, South York, interior view.....	383	Patents, decisions relating to.....	385
Dwellers, cave, in Mexico.....	384	Piemonte, Italian cruiser.....	388
Engineers, Am. visit to London.....	384	Pipes, water, standard.....	388
Exhibition, Paris.....	385	Plant, border.....	386
Explosive, new.....	388	Plante, Gaston.....	386
"Fault" in an ocean cable.....	387	Poisoning, lead.....	389
Floors, painting.....	393	Protector, sole, Lang's.....	386
Gale, and, New York.....	385	Puritan, new steel steamer.....	388
Gauge, surface, micrometer.....	383	Registers, physicians, for census.....	388
Hanger, electric lamp, Bucksey's.....	386	Schools, gov't., in China.....	392
Inventions, engineering.....	394	Ships, war, American and Italian.....	384
Inventions, index of.....	395	Signals, time, by magnesium.....	385
Inventions, mechanical.....	394	Steamers, British Canadian.....	389
Inventions, miscellaneous.....	393	Steel process, new.....	389
Johnstown, destruction of.....	388	Theories, earth, connection.....	388
Jurisdiction, medical, congress.....	393	Trees, falling, by electricity.....	389
Lathe, hand, universal.....	383	Tube, postal, Dover-Calais.....	382
Light and electricity.....	389	University, Clark.....	389
Lock, freight car, Frost's.....	386	University, Purdue.....	392
Locomotives and cars, buried.....	383	Vibrations, telephone, visible.....	388
		Wages, how to increase.....	392

## TABLE OF CONTENTS OF SCIENTIFIC AMERICAN SUPPLEMENT No. 703.

For the Week Ending June 22, 1889.

Price 10 cents. For sale by all newsdealers.

	PAGE
I. BIOLOGY.—Odoriferous Insects.—The perfume of insects.—Inter- esting notes on its observation in the field and its bearing upon the life history of the insect itself.....	11287
II. BOTANY.—The Gathering of Plants for the Herbarium.—A very practical paper on the collection and preservation of botanical specimens, with details of the plant presses, drying apparatus, etc. —3 illustrations.....	11287
III. CHEMISTRY.—Steam Suction Blast and Still.—An apparatus for use in pharmaceutical laboratories in the distillation of medi- cal and other products.—1 illustration.....	11232
IV. ELECTRICITY.—Power Test of the Datt Electric Railway at Asbury Park, N. J.—By F. E. IDELL, M. E.—A full and detailed de- scription of the recent tests of the Datt electric railway, with a view to the determination of its capacity and economy.....	11231
Simple A. C. Lamp.—A new electric lamp for the produc- tion of the electric arc.—2 illustrations.....	11232
V. GEOGRAPHY.—The Great Deserts of the Earth.—By JOSEPH F. JAMES.—A vivid description of the desert regions of the globe, giving a most interesting portraiture of these hitherto almost undescribed regions.....	11224
The Terrestrial Globe at the Paris Exposition.—A very full de- scription of the construction of the immense globe, over 125 feet in circumference, its framework, and the peculiarities of the building containing it.—3 illustrations.....	11223
VI. HYGIENE AND PHYSIOLOGY.—Dangers of Carbon Monoxide. —The report by Professor W. P. MASON upon the fuel gas acci- dent in Troy, New York, on January 6, 1887, giving an analysis of the gas and the features of its poisonous action, and of the autop- sies of the victims.....	11238
How Deaf Mutes are Taught to Speak.—An interesting and graphic account of the modern method of instructing deaf mutes in the production of articulate speech.—2 illustrations.....	11236
Walking Epilepsy.—A strange variety of epilepsy, with accounts of a victim of the disease as presented and investigated at the Salpetriere.....	11238
VII. MATHEMATICS.—Instruments for Drawing Curves.—By Prof. C. W. MACCORD.—A very ingenious device for drawing the curve of sines.—Fully described and illustrated.—9 illustrations.....	11233
VIII. MECHANICAL ENGINEERING.—Note on the Momentum of Steam in Steam Pipes.—By Prof. H. E. DENTON.—A very curious investigation of the mechanics of steam.—The production of pressure by momentum.—2 illustrations.....	11231
Otto Patent Wire Ropeway.—A very exhaustive description of a railway now in use at the Götteseken Colliery for transporting quantities of coal across the open country.—24 illustrations.....	11226
Some of the Big Things now Accomplished by the Manufactur- ers of Iron and Steel.—An abstract of a recent lecture by Sir JAMES KITSON, before the Iron and Steel Institute of Great Britain, describing some of the great metal-working machines of the world, giving a graphic review of modern progress.....	11230
IX. MICROSCOPY.—Zeiss' Apochromatic Objectives.—By Dr. OTTO ZACHARIAS.—A full review of the recent productions of the famous optician's laboratory, with details of the advantages ob- tained by the use of the new lenses.....	11235
X. MISCELLANEOUS.—A Conference of Representatives of Ameri- can Powers.—An interesting conference, to meet on October 4 of the present year, between representatives of the republics and governments of the western world.—The scope and probable function of the meeting.....	11234
The Old Oaken Bucket.—A very amusing parody upon the famous poem of Woodworth, revealing the malaria and impuri- ties of the old-time well.....	11234
XI. PHYSICS.—Apparatus to Illustrate the Influence of Pressure on the Volatilizing Point of Ice, and Other Phenomena.—By Prof. SIDNEY YOUNG.—An interesting series of experiments, with the description of an apparatus for performing in the line of Carnel- ley's "hot ice."—A valuable contribution to experimental work.— 1 illustration.....	11235

## AMERICAN AND ITALIAN WAR SHIPS.

No person in the United States having been found with ability sufficient to design and draw plans for fast and powerful war ships, the late Secretary of the Navy, Mr. Whitney, bought some plans of an Englishman, and for them paid a large sum.

These were substantial duplicates of the plans of a ship previously built in England, and on the lines so obtained the American cruiser Charleston has been built. In the meantime, and in fact in less time than it took our authorities to dicker for old drawings and copy a built ship, the Italian government ordered and has completed the construction of a new cruiser, on new plans, and the new vessel, although smaller than the Charleston, is superior in speed and power of armament. In fact, the velocity of the Piemonte surpasses our much-bragged-of torpedo boat Vesuvius. The latter made 21½ knots per hour; the Piemonte, 22 03 knots. The Charleston, 3,700 tons, it is hoped may reach 19 knots, but probably will not.

The much-vaunted prowess of our Vesuvius in being able, by her superior speed, to choose her position and destroy the strongest enemy at her leisure is knocked on the head. The new Italian ship can do this little job, not the American. Every one of the new ships built and those now being built by our government can be outsailed and probably overcome if attacked singly or in pairs by the Piemonte. It is humiliating to confess, but it must be admitted, the United States government is at the present time so utterly lacking in naval enterprise and knowledge that it cannot build, and cannot even order plans from abroad on which to build, new ships of the latest and most effective type.

We give in another column an account of the Piemonte as an example of the latest triumph in naval architecture, from which it is to be hoped our home authorities may derive useful instruction.

## THE NEW MAUSOLEUM.

"The new system for the sanitary disposition of the dead in the new mausoleum" was explained in the lecture room of the Academy of Medicine one evening last week, the stereopticon being used to advantage as a means of illustration. The dangers of the present system of burial were pictured, and, indeed, if the half of what was urged against it is true, it is pernicious in the extreme, being, so it would appear, a menace to the health of the living, especially those of feeble constitution or temporarily ailing, a concession to false sentiment, a relic of an unscientific and rude age.

The "new" mausoleum, the prime feature of the project to supplant the cemetery, is not, in its more important features, at all similar to that erected more than three hundred years before the Christian era to receive the body of King Mausolus, and from which this system of mortuary structures takes its name. That was intended for one, as, curiously enough, the termination of the name of him whose body was thus originally disposed would signify; and save that the body was sealed in stone, no further precaution was taken against contamination of the air than now obtains in the ordinary vault.

The "new" mausoleum is designed to contain about 40,000 bodies, to preserve them, though dead, in fair semblance of what once they were, and, best of all, to save the ground and its waters, and the air as well, from that wholesale contamination which the present system is said to breed. It is a remarkable fact that our Puritan ancestors, proverbial as they have become for sound common sense and reasonable practices in all else, selected eminences, more especially hill-tops, for their graveyards and cemeteries, the later generations following their lead in this as in many other things. Thus it is that in New York we have Trinity churchyard on the top of a hill; even the newer Trinity cemetery on Washington Heights is on an elevation. Greenwood cemetery, in Brooklyn, is on the crown of a broad hill. Such situations, it is said, are the very worst that could be selected, when the health of the living is considered, because of the water soaking through the ground, there to gather contamination and disease and bear it downward for distribution among the habitations.

Desiccation, that is the principle of the new system, the fluids and gases of the body, constituting 70 per cent of its whole volume and the sole cause of putrefaction, being slowly but surely dissipated. The receptacles, arranged singly and in family groupings and chambers, have only two small openings each; one by which the artificially dried air may enter, and another to allow of communication with the furnace in the sub-cellar. The dry air, entering, charges itself instantly with the vaporized water and gases, passing through pipes to the furnace, being there purified by fire and then forced outside, with no evidences of corruption remaining in it.

As to the condition which constant currents of dry air induce, a photograph was exhibited of a pilgrim which some travelers had come upon among the arid mountain plains of the Himalayas. Apparently exhausted from lack of water, he had sunk down upon the ground, leaned against a rock, and died; his head

thrown back, his mouth open. For many years, it is said, the body of the man had remained thus intact, unmistakable evidences of the fact being at hand. Yet, if the photograph is to be relied upon, there were no observable evidences of death save the stiffness of the pose, the flaccid give of the muscles.

In the "new" mausoleum the advanced scientific knowledge of the day will be utilized to its best; and judging from examples that have come down to us through the ages and similarly treated, intentionally or accidentally, there is reason to believe that the dead of the new mausoleum may readily be made to retain symmetry of feature and natural expression for centuries, and remain wholly inoffensive to sight or smell.

Included in the proposed plan is a system of delicate electrical wires, to be attached to the limbs, where any doubt remains as to the actual presence of death; the apertures of the receptacles being always open, suffocation cannot take place, and the slightest movement of the wires will serve to ring a bell in the watch room.

## The Visit of American Engineers to London.

Our readers, says *The Ironmonger* of June 1, will learn with interest that a party, numbering probably 220, being members of American societies of civil, mining, mechanical, and electrical engineers, accompanied by 50 ladies, are expected to reach Liverpool on or about June 5, and London a week later, where they intend to remain together as a body for a few days. Local committees have been formed at Liverpool and at Manchester, where arrangements are in progress for the inspection of engineering works on the day, or days, that may be spent in those cities, and the Mayor of Liverpool has invited the whole party to a conversation in the City Hall on the evening of Thursday, the 6th. On Friday, the 7th, members of the party will be entertained by the London and Northwestern Railway Company at Crewe, by the Midland Railway Company at Derby, and, in all probability, by the Lancaster and Yorkshire Railway Company at Horwich. The Whitsuntide recess will be spent in tours arranged by the London and Northwestern Railway Company and by Cook's agency. On Thursday, the 13th, the whole of the gentlemen will be entertained by the members of the Institution of Civil Engineers at dinner, which will take place in the Guildhall of the City of London, by the express sanction of the Lord Mayor, Aldermen, and Common Council. On the morning of the same day the visitors will be admitted to the Houses of Parliament by permission of the Lord Great Chamberlain. Her Majesty the Queen has been graciously pleased to allow the entire party to visit Windsor Castle and its surroundings on Saturday, June 15, and St. James's Palace, Buckingham Palace, and the Royal Mews on Monday, June 17. The Archbishop of Canterbury has acceded to a request to allow the members of the American engineering societies and their friends to be shown over Lambeth Palace on Tuesday, June 18. Excursions up and down the River Thames will be organized, and various privileges will be granted in order to render the visit a memorable one. The Institution of Civil Engineers, with their well known public spirit and hospitality, are actively exerting themselves in the matter.

## Cave Dwellers Found in Mexico.

A dispatch from Deming, New Mexico, says: "Lieutenant Schwatka has arrived here. His party has been successful beyond expectations in their explorations, and especially in Southern Chihuahua, where living cliff and cave dwellers were found in great abundance, wild as any of the Mexican tribes at the time of Cortez's conquest. The abodes they live in are exactly similar to the old, abandoned cliff dwellings of Arizona and New Mexico, about which there has been much speculation. It was almost impossible to get near them, so wild and timid were they. Upon the approach of white people, they flee to their caves by notched sticks placed against the face of the cliffs, if steep, although they can ascend vertical stone faces if there are the slightest crevices for their fingers and toes.

"These cliff dwellers are sun worshipers, putting their new-born children out in the full rays of the sun the first day of their lives, and showing many other forms of devotion to the great luminary. They are usually tall, lean, and well-formed, their skin being a blackish red, much nearer the color of the negro than the copper-colored Indian of the United States.

"Schwatka claims that nothing has heretofore been known about these people, except by the half-Indian mountain Mexicans, and thinks his investigation will be of immense anthropological and archæological value. He estimates the cave and cliff dwellers to be from 3,000 to 12,000 in number, armed only with bows, arrows, and stone hatchets."

The tinfoil so commonly used to wrap Neufchatel cheese, chewing gum, various kinds of candy, and all kinds of chewing tobacco, is said to be dangerous on account of the lead in it. Its use for wrapping articles of food has been forbidden in France.

## TIME SIGNALS BY THE MAGNESIUM LIGHT.

To the Editor of the Scientific American:

Having recently seen a magnesium flash light used for instantaneous photography, it occurred to me that the intense light produced could be utilized to advantage for distributing standard time signals by night. I decided to test the principle in a practical manner, and have obtained some very satisfactory results. The ordinary flash lamp, as made for photographic purposes, is an alcohol lamp giving a large flame through which a charge of magnesium powder is blown by means of a rubber bulb held in the hand. On pressing the bulb the magnesium is instantly ignited by being brought in contact with the alcohol flame. A lamp of this kind was fastened to a suitable frame, to which was attached a common telegraph sounder. A heavy weight was suspended over the bulb of the flash lamp in such a manner that it could be instantly released by the action of the sounder, thus depressing the bulb and firing the magnesium. The apparatus was connected with the signal circuit of the standard clock and a series of experiments was made. By previous arrangement the signals were observed by Mr. H. H. Clayton, of the Blue Hill Observatory, at a distance of twelve miles, and were seen with great distinctness. Rough observations showed that the time lost in the action of the firing mechanism was less than 0.4s. This error was nearly constant, and can be rendered practically inappreciable by properly constructed apparatus, specially designed for the purpose. The flash light would have the advantage of being visible to the unaided eye at a much greater distance than a time ball.

Being necessarily used in the evening, it would be seen by many whose only leisure time is after working hours. A flash signal fired from a hill or from the top of a high building would be visible in all directions for many miles. The cost of the apparatus is very small when compared with that of the time ball. I think that a system based on the principle which I have described will recommend itself to those interested in time service matters as cheap and effective.

WILLARD P. GERRISH.

Harvard College Observatory, June 8, 1889.

## The Paris Exhibition.

[SPECIAL CORRESPONDENCE OF THE SCIENTIFIC AMERICAN.]

PARIS, June 1, 1889.

Some idea of the immensity of the Paris exhibition may be gathered from the fact that, notwithstanding the five days I have spent in the exhibition since it opened, I have not as yet come across the exhibits of agricultural machinery. At a rough guess I should say that to walk through the aisles straight ahead, without turning back, would involve a tramp of at least a dozen miles, and one of the difficulties is to know where to begin and where to leave off without missing items of importance. Resuming, however, my general survey of the principal buildings, one cannot fail to be struck with the amount of gilding apparent everywhere. The interiors of the domes of the buildings are ablaze with it, and to judge from the exhibits we may call this the gilt year. In the Austria-Hungary section of ceramics, glass, etc., which is one of the most charming and artistic sections of the whole exhibition, the gilt gives a distinguishing tone to the exhibits as a whole, the effect being soft and elegant. Refined beauty, indeed, seems to pervade this whole section, which casts all its competitors entirely into the shade, and makes the visitor feel dissatisfied with them. This effect is obtained without the vulgar glare that usually attends the employment of much gold, by means of the patterns, which are small and intricate, after the East Indian style. In the Belgian section, gold again predominates, the ground being white and sufficiently prominent to give a distinctly whitish character. The exhibits of the Pays Bas in this section are somewhat meager, and there is more vacant floor space than needs be. There are some excellent tapestries in the Belgian department, but in this part of the exhibition a good portion of the space is not yet opened to the public.

The Australian colonies have a fair exhibit, but not any better than they had at the centennial. We find here the usual models of huge gold nuggets and specimens of the fauna and flora of the colony, with some very fine photographs of the great trees, the largest of these photographs measuring about 4 feet by 2½ feet, and showing a tree 326 feet high. The quantity of statuary in the exhibition is very remarkable. Indeed, in one side of the quadrangle of the grounds inclosed by the main buildings and ending at the Eiffel tower, I counted 125 statues, a large proportion being in front and in the neighborhood of the refreshment rooms. A great many of these exhibits are in an unfinished state. Hence nothing can be said about them; but some of those that are apparently finished are sadly marred by faulty joints of arms, legs, etc., where those members are affixed to the main body. Those who have seen the Albert memorial in Hyde Park will remember to what a painful extent this same defect is apparent, and visitors to Paris will not fail to observe it upon seeing the beautiful groups of

statuary in front of the Grand Opera House. Surely there is no great difficulty in remedying so demoralizing a blemish.

As one enters the hall of statuary in the Palais des Beaux Arts, the *coup d'œil* is very impressive indeed, and it is very difficult to define whence the impressiveness arises. No doubt the immense size of the hall with nothing but statuary in it has something to do with it, as also has its great height, but be the cause what it may, it is a majestic as well as a beautiful display. The galleries of this hall are not as yet opened to the public, nor indeed are there any exhibits in them, except it be some tapestries that hang against the wall. There are in this section about twenty tapestries (mostly of the last century and upon biblical subjects), and these will form very attractive objects to American visitors. In some cases plaster casts are doing service as representatives of masterpieces that could not be moved to the exhibition, a case in point being "La Jeunesse" by Antonin Cartes, the original being in the Luxembourg Museum. Among the prominent statuary, the following may be mentioned: A bronze group by A. Cain, of a life size rhinoceros and two tigers, the former having crashed his horn into the side of one of the tigers, which lies on its back with its claws helplessly distended, while the other is vainly trying to bite through the mail of the rhinoceros. This is an exceedingly effective and fine production, as is also another exhibit of the same artist, representing an alligator in the jaws of a lion.

There is a full size statue of Mons. Chevreul, that is very life like and natural, and a bust of Henry George hidden away in a corner. A plaster statue entitled "Berger and Sylvain," which belongs to the government, and was in the salon of 1884, is an artistic piece of work, but a bad joint in the muscle of the right arm is a prominent blemish. Some of the plaster models are very large, one I noticed being about 14 feet high and 8 feet wide. The subject is the return of veterans from the war. The main figures are two soldiers embracing each other amid a profusion and confusion of warlike implements, with two women drawing together with outstretched arms the folds of battle flags whose staffs are in the hands of some soldiers beneath; the size as well as the execution of this exhibit make it notable. Another exhibit, a woman mourning over a tomb, is very effective, and reminds one very forcibly of the bronze statue (of similar *motif*) in Woodlawn Cemetery, N. Y. "Moliere et sa Servante," from the salon of 1886, is also beautifully executed, but the sheet of paper Moliere holds in his extended hand is too small, so that the servant, instead of looking at it, is looking clear over it. The pen Moliere holds in his right hand is a veritable quill, coated with plaster, part of which has fallen off, exposing the quill—a defect which will doubtless be remedied in due course. There are several good representations of the "femme furieuse" and of the "femme militaire."

A notable exhibit in this department is some tinted busts and statues by A. Wiezenberg, "Rome, 1889." Gibson's tinted Venus created, it will be remembered, quite a stir in the artistic world in 1862, at which date it was exhibited in the London Universal Exhibition. The effect of the tinting has been somewhat marred by a blue vein in the marble, running almost around one thigh. Wiezenberg's exhibits are, however, of a very clear, pure marble, and are in some cases so slightly tinted that the casual observer does not for the moment discover the tinting. The best specimen of this exhibit is a life size bust entitled Mapye A. She has a faintly tinted bandanna around her head, and around its edges are two fine gilt lines. Similar lines run around the collar of her bodice. Her eyes are very faintly tinted, giving them an exceedingly natural appearance, and one has to inspect very closely to discover the tinting. The execution of this exhibit is very charming, the face not perhaps so beautiful, but so expressive, natural, and warm, with an individuality that delights the beholder. Undoubtedly this will be a general favorite with the public at large.

The same artist exhibits a life size "Germania," in which the hair is plainly and the eyes slightly tinted, but the latter not all over, the term "shaded in parts" perhaps being a more correct one. A third example is "Ideal," in which the eyes are so plainly tinted that it gives the idea somewhat of an artistic trick. Her tiara is gilded, and the general effect of the whole is not altogether good. A fourth exhibit is "Reale," whose hair is very effectively tinted, and the eyes are good at a distance. The first named is by far the best, although only a bust, while the others are full figures.

Near this group, and one each side of the doorway, are two exhibits that are good in their way. Both are in terra cotta and by Holden Hertzberg. The best is a "Whistling Boy." The position in which he is placed is an exceedingly happy one, for, being close to the door, he looks as though he had just entered it, and was taking a general survey of the hall. He stands with both feet apart, his hands in his trousers pockets, his back bent slightly in, and the whole pose is of a happy-go-lucky yet contemplative style that is very taking. It is difficult to conceive that this is an artist's conception, because of the peculiar individuality of the face,

which has a frank, trustworthy expression, combined with the acute intelligence that is more often found in the good street boy than in the good school boy.

A companion exhibit on the other side of the same doorway represents a boy with the two forefingers of his left hand in his vest pocket and his right hand in his trousers pocket, while his eyes are partly closed and looking sideways. As there is no title to this, I presume it is expected to tell its own story, but it does not. The attitude would interpret very well into "Can I afford to buy it?" or "Can I scrape together enough money to buy it?" but there is an acute cunning in the face, and the strained side look in the eyes would rather suggest (outside the position of the hands), "I'm a-watchin' of yer." The nose is sharp, the face somewhat lean, and the lips thin, giving an idea of general untrustworthiness. The beauty of the human form divine is marred in some few instances by defects in the coloring of the marble being so painfully marked that tinting the blue blotches would seem not only permissible, but decidedly necessary.

A very effective plaster model represents a large gorilla who has seized a female figure, and his right paw grips her from the upper rib, round under the arm, pressing deeply into the flesh. He is leaning forward in an attitude of defiance, ready to do battle for his prize, and to spring at an assailant who has shot an arrow through the flesh on his left side. The female is forcing herself from his embrace with all the life that is left in her, her hands being partly buried in the flesh of his neck. The strength and ferocity of the gorilla is beautifully portrayed in this work, around which a group of visitors is always found. The sculptor (E. Fremie) was awarded for it a medal of honor at the Paris salon. One more striking work of art may be noticed before concluding a cursory glance at this hall, and it is entitled Lutinerie. On a lion's skin reclines a nude nymph who has partly raised herself on one arm. Her right hand is extended, and has by the ear a young satyr, who has evidently been caught in the very act of trying to take her by surprise. The expression on both faces is admirable, the one saying, "Ah! I've just caught you, sir!" the other has two expressions, one showing that his ear is being pulled much harder than he cares to confess, and the other saying, "Let go! It's all right. I know you don't really mean it." The sculptor is Jean de Villeurs.

The exhibits of painting are arranged in rooms or *salles*, but no seats are as yet provided for them, and from the narrowness of the doorways, considerable crushing must inevitably occur on days when the attendance is large. Of course there are some fine pictures, a great many fine pictures, in fact, but there are also some that are otherwise, among which I should place a picture numbered 03 in *salle* No. 1. It is a female whose dress has an unnatural satiny gloss, and is dotted over with vertical splashes of many colored paints. Her face is covered with a remarkably pronounced yellow that could not possibly be produced naturally, nor indeed artificially by any ordinary means save by a heavy coating of yellow ochre. The splashiness of the dress leads one to suppose that this painting is one of that new order of which something has been heard in London lately, and of which it has been said that, if you look at the splashes long enough, it breaks on you like a revelation that a beautiful picture is emerging from them. I have not tried this prolonged gazing, as a short gaze is quite painful enough. In connection with pictures, one cannot altogether ignore the matter of picture frames. All very large picture frames are of gilt moulding, of course, but in the matter of smaller ones, say under three feet, I found more artistic frames and a greater variety in New York (on my visit last December) than I find here. This may, of course, be partly on account of the gilt craze (which exists not only in picture frames, but also in mirror frames and over mantels, in England), which does not seem to have extended to the United States.

JOSHUA ROSE.

## DECISIONS RELATING TO PATENTS.

U. S. Circuit Court.—Southern District of New York. *YOUNG et al. v. FOERSTER.*

PATENT STONE SAWING MACHINE.

Cox, J.

A machine purchased of the complainant, the patentee, by the employer of the defendant, was repaired and its construction somewhat changed by the defendant in his capacity as an employe of the purchaser. Held that the purchaser was at liberty to repair and improve it within the limits of his contract, and that so long as the identity of the machine was not destroyed, its owner had the right to discard useless parts and add new ones which might improve its action.


One who has a license to use the whole of a machine does not become an infringer by the use of a part only.

To expel mosquitoes, take of gum camphor a piece about one-third the size of a hen's egg, and evaporate it by placing it in a tin vessel and holding it over a lamp, taking care that it does not ignite. The smoke will soon fill the room and expel the mosquitoes, and they will not return, even though the windows should be left open all night.



## AN IMPROVED END GATE FOR VEHICLES.

The illustration herewith represents a wagon end board which has been patented by Mr. Theodore B. Burr, of Harlan, Iowa. It is adapted to be firmly locked in upright position, readily carried to a horizontal position over the wagon body for dumping, as shown in dotted lines in Fig. 1, or placed in horizontal position for use as a scoop, as shown in Fig. 2, without the dismounting of the driver from the vehicle. A transverse plate is attached to the bottom of the body, at the end, with a gudgeon at each extremity. Strap




BURR'S END GATE FOR VEHICLES.

hinges attached to the end gate have a bearing upon the gudgeons, and jointed supporting bars connect the body and the end gate, stops on the side boards limiting the forward and rearward throw of the supporting bars, while a hinge on the outer face of the end gate has a detachable bearing on the keeper of the transverse body bar. The jointed supporting bars slide one upon the other at their pivotal point, and are pivoted at their outer ends to the body and to the end gate. When the end gate is to be used as a scoop-board, it is supported by the fully extended members of the supporting bars and the end hinges resting upon the gudgeons, together with the hinge bearing upon a strap plate. To uncover the end of the wagon body for dumping, the supporting bars are thrown upward to assume a perpendicular position, and the end gate is lifted up bodily, the hinges disengaging from the body plate, when the gate is carried up to the horizontal position shown in dotted lines.

## AN IMPROVED BOLTING CHEST.

A bolting chest designed to facilitate the cutting off of the product at any desired point in separating the fine flour, middlings, etc., is shown in the accompanying illustration, and has been patented by Mr. Hugh McEwen, of Tiverton, Ontario, Canada. The reel, covered with any desired number of bolt cloth, is attached to a central longitudinal shaft journaled in bracket bearings in the ends of the frame, one extremity of the shaft having a drive pulley. The posts of the frame are connected by four rods, upon which a cut-off is held to slide longitudinally, this cut-off consisting of a rectangular plate with a central opening to receive the reel. The covering of the bolt is made of closely woven cloth, secured rigidly to the inner faces of the posts, and also to the upper edge of the cut-off, whereby two compartments are obtained, one at each side of the cut-off, while below the lower rods connecting the posts the cloth is connected and carried downward in funnel-shape, the lower extremity of each funnel having a metal sleeve. The cut-off has one or more set screws for holding it in such position along the longitudinal



MCEWEN'S BOLTING CHEST.

rods as may be desired. The material to be bolted is passed into the reel by means of a suitable chute at the front of the machine, the tailings finding their exit through a chute at the rear, while the fine flour is passed through the reel at the forward end, and the middlings in the second compartment. As the chop approaches the center of the reel, and the grade of flour becomes more or less coarse, the separation desired may be varied by carrying the cut-off either forward or

backward, thus enlarging or diminishing the area of the bolt discharging into either one or the other compartment.

## Gaston Plante.

The well-known French electrician Gaston Plante died suddenly at the age of fifty-four. The principal work of Plante's life, says *Industries*, was his investigation into the voltameter, the practical result of which was the invention of the storage cell with lead plates. Plante experimented upon all conceivable metals and combinations of metals to be used for electrodes in voltameters, and the result of his numerous tests was to show that lead is, all things considered, the best active material from a practical point of view, though the amount of energy which he found possible to store per unit of weight was greater in the case of some other metals.

Like a true scientist, Plante gave his discoveries to the world without having patented his inventions, and others have reaped the benefit of his labors. The immediate cause which prompted him to undertake the long series of investigations was not the desire to find a storage battery, because in those days the application of dynamos to electric lighting was still unknown; it was the desire to study the effects of electric discharges of great quantity, which were not attainable with frictional machines and Leyden jars. The discovery of the lead accumulator was, so to speak, a by-product of his investigation. He also invented what he called the "machine rheostatique," being essentially a commutator which, on being turned by a crank, rapidly changed the grouping of the secondary cells from parallel to series.

Of late years Plante devoted himself almost exclusively to the reproduction of meteorological phenomena in the laboratory by electrical effects, and he succeeded in thus imitating hail, globular lightning, etc. His latest publication was a small book on this subject, and he has also contributed to the exhibition at Paris some very interesting apparatus and specimens in connection with this work.

## A BOOT OR SHOE SOLE PROTECTOR.

The accompanying illustration represents a device for protecting the bottoms of boots or shoes from being soiled when fitting or trying them on in a store. It forms the subject of a patent issued to Mr. Louis P. Lang, of Allegheny, Pa. The device consists of a longitudinally expansible and contractible bottom cover, made preferably of rubber webbing, of a length to take in the greater portion of the tread of the boot or shoe. Between two thicknesses of this elastic material is a metal plate, united intermediately of its length to the material, and secured to the front end of the material is a wire loop, to be entered between the upper and sole, so as not to be seen by the person trying on the shoe. Secured to the rear end portion of the cover are opposite side uprights, from which a rubber band is held to stretch around and hold the protector on the heel of the shoe. The device is adapted for ready application on a shoe being fitted without attracting the notice of the customer.



LANG'S SOLE PROTECTOR.

## Safe Transportation of Sulphuric Acid.

Herr Bickmann has patented in Germany a process for enabling sulphuric acid for manufacturing purposes to be safely transported. He takes advantage of a property of certain salts—of which alkaline sulphates are representatives—by which they give up their water of crystallization when heated and take it up again when cool; and he does so by mixing the salts in an anhydrous condition with a calculated quantity of sulphuric acid. The whole mass becomes granular, or may be formed into cakes; and when heated the whole liquefies and may be used as if it were sulphuric acid, for the presence of bisulphate of soda does no harm.


## Physician's Registers for the Next Census.

The superintendent of the U. S. census for 1890, Robert P. Porter, earnestly asks the co-operation of the medical profession throughout the country in the perfection of the mortality and vital statistics for the year commencing June 1, 1889. With this view "physician's registers" are being issued to all who can be reached, and physicians not receiving them are invited to send to the census office in Washington therefor, and aid the department, by their use, in obtaining more complete statistics as to the annual births and deaths. In 1880, 26,000 such books were filled up and returned to the census office, and nearly all of them found useful in the way designed.

*Myosotis alpestris*, Victoria, proves to be a perfect border plant in this latitude, hardy without protection and easily multiplied by division or from seed.

## AN IMPROVED LOCK.

A lock especially designed for use on freight car doors, wherein the parts are so constructed that the hasp may be secured to place by the lock itself, or by the ordinary form of padlock, is illustrated herewith, and has been patented by Mr. Haller C. Frost, of Farmington, Cal. The staple is held in place in the lock by a nut, and has an outwardly extending flattened head with a central aperture adapted to receive the bow of a padlock. The main body of the staple is preferably round, but it has recesses through its body adapted to receive a locking bar mounted above the staple and guided by brackets, this locking bar normally holding the staple in locked position by means of a spring bear-




FROST'S LOCK FOR FREIGHT CAR DOORS.

ing upon the top of the locking bar and secured to the lock case. The locking bar has an inclined shoulder directly opposite the keyhole, and the key is formed with a nose projection and an inclined face, whereby, when the key is inserted, the locking bar will be moved against the tension of the spring to release the staple, as shown in the sectional view, so that the staple may be turned to a position to permit the withdrawal of the hasp.

## ELECTRIC LAMP HANGER.

This device, shown in the accompanying illustration, invented and patented by Mr. John Bucksey, of No. 70½ Sparks Street, Ottawa, Canada, is simple and efficient in operation, elegant in appearance, and designed to save considerable labor in taking care of electric street lamps and expense for broken globes. The iron arm carrying the lamp is forked and is hinged to each side of the main post. The electric wires lead from insulators at head of post to insulators at the place of the hinge, and thence along the arm to the lamp, thus allowing the lamp to be raised or lowered without tension or slackening of the wires and permitting it also, if desired, to be raised, lowered, or locked in any position without being extinguished. To lower the lamp for cleaning, etc., the operator unlocks the box containing windlass at the foot of the post, inserts a crank and unwinds the drum, on which turns an endless cable. The lamp is thus lowered to position shown in the illustration, within easy reach of the operator, doing away with the necessity for climbing. The lamp being cleaned, etc., is once more raised into position, the crank is withdrawn, the door locked, and the operator goes on to the next lamp without loss of time. The drum or windlass operating the cable is simple and powerful in action, raising and lowering the lamp with ease, with-



BUCKSEY'S ELECTRIC LAMP HANGER.

out jerking, and preserves a perfect up and down tension on the lamp-holding arm at all times. Lateral rigidity is insured by the arm being divided and hinged to each side of the post. With a 12 foot arm hinged 19 feet from the foot of the post, the lamp can be raised to a height of 30 feet from the ground, and cannot be tampered with in any way. This mechanism, as will be seen from cut, works equally well with the wires overhead or underground.



## A "FAULT" IN AN OCEAN CABLE.

The value of laying ocean cables containing two cores was shown during the violent storm of November 25, 1888, when a fishing schooner about 26 miles from Gloucester, Mass., dragged her anchor for some distance until at last she hooked the Rockport cable of the Commercial Cable Company's system, riding to it for about forty-eight hours and producing the fault shown in the illustration. It was found when picking up the cable during the repair that she had dragged along it for some 400 yards, tearing off the outer covering of jute and compound, also one of the armor wires, rolling it up into a tangled mass and at last driving the end of the steel armor wire between the sheathing of the cable and through one of the cores, but leaving the other absolutely intact. With a single core cable of the ordinary type communication would have been interrupted until repairs were effected; but in this case, by means of the uninjured core, traffic was passing continuously with the exception of a few hours, during which the repair steamer had the cable cut in order to remove the fault. Considering the extreme violence of the gale and the large size of the vessel, it is surprising that the cable did not part.

The repair was made by the steamship Pouyer-Quertier, which was chartered for the purpose, as she was the only available cable steamer on this side of the Atlantic. Capt. S. Fossard, who commanded the steamer, showed such great skill in maneuvering her that although two and a half miles of cable was picked up and relaid across a tideway of four knots per hour, it was found, on completion of the repair, that the cable was only lengthened by a few yards.

The electrical department on board was in charge of Mr. Chas. Cuttriss, the company's electrician.

This remarkable "fault" has now been placed on exhibition at the Paris exposition.

We are indebted to the *Electrical World* for the cut and description.

## ASPIRATORS FOR LABORATORY USE.

BY GEO. M. HOPKINS.

Wherever a head of water of ten feet or more is available, an aspirator is by far the most convenient instrument for producing a vacuum for filtration and fractional distillation. It is also adapted to a wide range of physical experiments.

Besides the advantage of convenience and compactness the aspirator has the further advantage over piston




Fig. 3.—METAL ASPIRATOR. Fig. 6.—PLATE AND RECEIVER FOR ASPIRATOR.

air pumps in the matter of cost. They may be had at prices varying from \$1.50 to \$4 or \$5.

Two kinds are in general use—one of glass, known as Bunsen's filter pump, and shown in Figs. 1 and 2; the other of brass, shown in Figs. 3, 4, and 5.

The glass aspirator can be purchased of almost any dealer in druggists' sundries or chemical glassware. Any expert glass blower can make it in a short time.

This instrument consists of an elongated bulb terminating in a crooked tube at the bottom and having a tapering nozzle inserted in the top and welded. The lower end of the nozzle is located directly opposite and near the crooked discharge tube. A side tube is connected with the bulb at a point near the junction of the nozzle and bulb.

This aspirator is used in the manner indicated in Fig. 2, i. e., the upward extension of the





Fig. 4.—EXHAUSTING GEISSLER TUBE.

nozzle is connected with a tap by a short piece of rubber tubing, and the side tube is connected by a piece of rubber tubing, with the vessel to be exhausted. When the water is allowed to flow through the aspirator, it leaps across the space between the nozzle and discharge tube and carries with it the air from the bulb, which is continually replaced by air from the vessel being exhausted.

It is necessary to securely fasten the ends of the rub-



A "FAULT" IN AN OCEAN CABLE.

ber tube connected with the tap or the water pressure may force it off, thus causing the breaking of the instrument. To secure the best effects with this pump, it is necessary to connect a vertical tube 25 to 30 feet long with the discharge end of the pump.

The metallic aspirator shown in Figs. 3, 4, and 5 is of course free from all danger of being broken in use, and it has other qualities which render it superior to the glass instrument, one of which is a much higher efficiency, another is its ability to retain the vacuum should the flow of water be accidentally or purposely discontinued. It can be screwed directly on the water tap, and needs no additional pipe to cause it to work up to its full capacity; and where a head of water is not available, it may be inserted in a siphon having a vertical height of ten feet or more.

This instrument is made by Mr. E. C. Chapman, of Brooklyn, N. Y. Like all instruments of its class, it is based on the principle of the Giffard injector. Its great perfection, however, is due to Mr. C. J. Lawler and to its manufacturer. The construction of the aspirator is shown in section in Fig. 3. The water enters at A, as indicated by the arrow. The air enters at B, and both air and water are discharged at C. The water in going through the contracted passage forms a vacuum at the narrower part into which the air enters. The starting of the instrument is facilitated by a diaphragm which half closes the discharge tube. The water is prevented from entering the air pipe by a small check valve shown in the interior of the lateral tube. Much of the efficiency of this instrument is due to the accuracy with which the contracted passage is formed. A slight change in the shape of this passage seriously affects the results.

The vacuum produced by this aspirator is equal to that of the mercurial barometer, less the tension of aqueous vapor. That is to say, when the barometer is at 30 inches, the vacuum produced by the aspirator will be about 29½ inches. Such a vacuum can be produced by water under a pressure of five and one-half pounds.

In Fig. 4 is shown the aspirator applied to a Geissler tube. It quickly exhausts an 8 inch tube, so that the discharge of an induction coil will readily pass through. By placing a tee in the connecting pipe, the Geissler tube can be filled with different gases. Each will exhibit its peculiar color as the spark passes. The vacuum is not high enough for a perfected Geissler tube, but it is sufficient for the greater part of vacuum experiments. The aspirator can be arranged to produce a continuous blast sufficient for the operation of a blowpipe, and for other uses requiring a moderate amount of air or gas under pressure.

The method of accomplishing this is illustrated in Fig. 5. The instrument is arranged to discharge into a bottle or other vessel having an overflow, and the

air for the blast is taken out through the angled tube inserted in the stopper of the bottle. The amount of air pressure is regulated by the water pressure and the height of the overflow pipe.

For many vacuum experiments a plate provided with a central aperture, and having a tube extending from the aperture to the edge of the plate, will be found useful. The tube is provided with a suitable valve, which closes communication with the aspirator, and which also serves to admit air, when required, to the receiver fitted to the plate. This plate and various accessories are like the plate and accessories of a piston air pump. Communication is established between the tube of the plate and the aspirator by means of a pure rubber tube which is practically air tight.

## New Metals.

According to the *Chemiker Zeitung* (Coethen), at the last sitting of the Russian Mineralogical Society, K. D.

Chrutschoff demonstrated the existence of a new metal which he has just discovered, and to which he gives the name russium. It approximates closely to thorium, and is one of the bodies whose existence was foreseen by Prof. Mendelejeff. We learn also that Dr. Kruss has named the metal which he has detected along with nickel and cobalt, gnomium.

## Not Bad Advice.

Mr. Mechanic, if your mind runs to the invention of "small things," as they are often called in unwise contempt, you may hit upon a "big bonanza." Westinghouse has made \$20,000,000 out of the air brake. It was called at first a "small thing," using air in that way, but it has panned out well. Other "small things" have rewarded mechanics well. The lead pencil rubber tip cleared its inventor \$100,000; the metal rivet or eyelet for miners' coat and trousers pockets brought its inventor a fortune; boot and shoe heel and sole plates of metal cleared \$1,250,000; the glass bell inverted over lamps and gas jets cleared a fortune; the simple plan of fastening powdered emery on cloth made a fortune; the roller skate cleared \$1,000,000 before the craze died out; the gimlet screw realized millions; copper tips for shoes netted millions; the simple needle




Fig. 5.—BLAST PRODUCED BY THE ASPIRATOR.

threader netted \$10,000 a year; toys and playthings have cleared thousands; the ball with the rubber string brought an income of \$50,000 a year; the "Dancing Jim Crow" netted \$75,000 a year; Pharaoh's serpents cleared \$50,000; the "wheel of life" cleared \$50,000; the chameleon top cleared a fortune; the "Pigs in Clover" puzzle has within one year made its inventor a fortune; the pencil sharpener cleared a fortune. Hundreds of "small things" have turned out well. If you have an idea, bring it out and let the busy and inquisitive world see it. The mechanics who have been enriched by little inventions far exceed in number those who have reaped fame and fortune by great inventions. Put on your thinking cap, Mr. Mechanic, and dive into the world of possibilities. The fortune is there if you only know how to find it.—*The Iron Industry Gazette*.




Fig. 1.—BUNSEN FILTER PUMP.—Fig. 2.

**The New Steel Steamer Puritan.**

The new and magnificent passenger steamer *Puritan*, the latest and finest example of American marine architecture, went on her first public trial trip, down New York harbor, on the 13th of June. The trip was a great success. She belongs to the Fall River line.

The model and general plans were designed by Mr. Geo. Pierce, Supervisor of Steamers of the Old Colony Steamboat Company; the details of steel hull, etc., by Mr. Edward Faron, of the Delaware River Ship and Engine Building Company. The hull was built at Chester, Pa.

Her principal dimensions are as follows: Length over all, 420 feet; length on the water line, 404 feet; width of hull, 52 feet; extreme breadth over guards, 91 feet; depth of hull amidships, 21 feet 6 inches; height of dome from base line, 63 feet; whole depth, from base line to top of house over the engine, 70 feet. Her total displacement, ready for a trip, is 4,150 tons, and her gross tonnage, 4,650 tons.

The *Puritan* is fireproof and unsinkable. She has a double hull, is divided into 59 watertight compartments, 52 between the hulls and 7 by athwartship bulkheads. Her decks are of steel, wood covered. Her masts are of steel, and hollow, to serve as ventilators, and are 22 inches in diameter.

Her wheels are of steel, 35 feet in diameter outside the buckets. The buckets are 14 feet long and 5 feet wide; each bucket of steel, seven-eighths inch thick, and weighing 2,800 pounds, without rocking arms and brackets attached. The total weight of each wheel is 100 tons. The two together are in the nature of enormous flywheels for the machinery. The wheels are of the kind known as "feathering," and the engine will drive them at the rate of 24 revolutions a minute.

Her rudder is 14 feet 6 inches fore and aft, average height 13 feet, whole length of stock 18 feet. It is made of steel, filled with wood between the plates, and weighs nearly 30,000 pounds.

Of her machinery, boilers, etc., Messrs. W. & A. Fletcher & Co. (North River Iron Works) were the builders, and they were also the contractors for the building and completion of the ship in every part.

The *Puritan* has a compound, vertical beam, surface condensing engine of 7,500 horse power. The high-pressure cylinder is 75 inches in diameter and 9 feet stroke of piston. The low-pressure cylinder is 110 inches in diameter and 14 feet stroke of piston. A horse and wagon could be driven through this cylinder if laid on its side. The surface condenser has 15,000 square feet of cooling surface and weighs 53 tons. Of condenser tubes of brass there are  $14\frac{1}{2}$  miles in the *Puritan*. Her working beam is the largest ever made, being 34 feet in length from center to center, 17 feet wide, and weighing 42 tons. When it is considered that the section of beam strap measures  $9\frac{1}{2} \times 11\frac{1}{4}$  inches, one may get an idea of the enormous strain and the strength of resistance of this beam. The main center of the beam is 19 inches in diameter in bearing. The shafts are 27 inches in diameter in main bearing and 30 inches in gunwale bearing, and are the largest ever made in this country. They weigh 40 tons each. The cranks weigh 9 tons each. The crank pin is enormous, the bearing being 19 inches in diameter and 22 inches long.

The ponderous machinery of the *Puritan* is handled by a small supplementary engine. The galleys frame is of heavy steel plate, and by its angles easily supports the enormous working beam.

She has eight steel boilers of the Redfield return tubular type, and the maximum working pressure is 110 lb. to the square inch. Six of these boilers are 18 feet 1 inch in width and 15 feet 2 inches long; the other two are 10 feet wide and 14 feet long. Each of the wide boilers has two shells; the narrow boilers have one each, 7 feet 8 inches in diameter. The boilers contain 850 square feet of grate surface and 26,000 square feet of heating surface. The products of combustion pass through two superheaters, 8 feet 10 inches inside diameter and 12 feet 4 inches outside diameter by 12 feet high; thence into two smokestacks, the top of each being 101 feet 1 inch from the keel. The fire room is  $78 \times 12\frac{1}{2}$  feet. There is a donkey boiler on the main deck for auxiliary purposes. Her steam steering apparatus has engine of two cylinders, each 24 inches diameter, 18 inches in stroke; this engine alone is powerful enough for a big tug boat.

There are two centrifugal circulating pumps, each capable of throwing 10,000 gallons per minute. Besides these there are three other large pumps, with a combined capacity of 2,000 gallons per minute. Novel features are the three steam capstans, one forward and one on each quarter, to be used in docking the boat; each capstan has a double cylinder engine, each cylinder 12 inches in diameter and 14 inches stroke. She has two Sturtevant blowers, furnishing fresh air for fire room, each capable of 50,000 feet per minute. She will burn about 120 tons of coal on the trip from New York to Fall River and back.

The hurricane or extreme upper deck is open for passengers, and has a promenade entirely around its outer edge. On the saloon deck there is a continuous promenade entirely around its area, outside the wheels. The outer promenade space of the hurricane deck is 10 feet

wide and 42 feet above the water-line. From this deck the most magnificent outlooks are afforded.

The dining saloon is 108 feet 4 inches in length, by 30 feet in width, and 12 feet in height.

From stem to stern, and in every nook and corner of the ship, the electric wire is to be found. In all, there are twelve miles of this wire, and, including annunciators, fire alarm, etc., there are twenty miles of wire on the ship, and twelve thousand feet of steam pipe. There are capacious gangways, grand and imposing staircases, heavy with brass and mahogany, lofty cornices, and ceilings supported by tasteful pilasters, the tapering columns of which, in relief, flank exquisitely tinted paneling throughout the length of her grand and minor saloons. And over all this artistic work and exuberant coloring, the incandescent electric light sheds its soft rays. Every convenience known to civilization, and which can contribute to the ease and comfort of the traveler on land or when afloat, is included in the internal arrangements of this floating caravansary. The artistic and luxuriant sense of the beholder is also abundantly appealed to.

The electric light plant of the *Puritan* is the most perfect of its kind, and its kind is of the best known. The system used is the Edison incandescent lighting, and it is furnished by the Edison United Manufacturing Company. The currents are generated by four dynamos of special type and construction, each having a capacity of four hundred lights, or a total of 1,600 lights as a safety load, but capable of maintaining 1,850 lights if required. The dynamos are located in the forward part of the boat, under the officers' cabin.

They are connected in pairs, the motor being supplied by two Armington & Sims special double engines of fifty horse power each, two of the dynamos being connected with each engine, and the two connected with each other by direct shafts, so that one or both dynamos can be used at will. The intention has been to make this the most perfect installation ever constructed, the test being higher than ever before required or given by any electric company.

For fire fighting, the *Puritan* is equipped with the most thorough and complete apparatus, including steam and hand pumps, extinguishers, tools, etc. There are fifty connections to the steam pumps, in different parts of the boat, for fire purposes exclusively. She has three hand pumps, and these are of unusual size. She has eight Harkness fire extinguishers, and carries 175 fire pails and 36 axes distributed through the ship at convenient points.

The life-saving service and appliances of the *Puritan* are also of the best approved establishment and effectiveness. As is the case of all the boats of the Fall River line, the life-saving crew is appointed with sole reference to this service, and all its drill and occupation are in the way of perfecting methods in this department.

As an adjunct of the life-saving service, and for use in case the whole ship's company should be threatened, the *Puritan* carries a dozen 26 foot life-boats, 12 life-rafts, and 1,400 life-preservers.

The ornamentation of the *Puritan* has been in charge of Mr. Frank Hill Smith, of Boston, and to him are due the artistic effects in design and finish that this ship presents. The details of architecture, ornament, painting, etc., have been worked out and applied by him.

From floor to dome of the saloon deck every foot of surface of the walls, galleries, and ceilings presents a marvel of decorative finish, artistic in style and design, exquisitely tasteful in coloring, and blending the finest ornamental effects in rich succession.

**The Italian Cruiser Piemonte.**

In the latter part of 1884 the performance of the Chilean cruiser *Esmeralda*, constructed by Sir W. G. Armstrong, Mitchell & Co., attracted general attention. She was a vessel of 3,000 tons displacement, carried as armament two 25 ton guns, six 6 in. guns, and a number of Hotchkiss and Gatling guns, and she attained the then unprecedented speed of  $18\frac{1}{4}$  knots. Her steam trials were attended by Mr. George Rendel, by whom she had been designed, but who had recently severed his connection with Sir W. G. Armstrong, Mitchell & Co., and had become a civil lord of the Admiralty, by Admiral Brandreth (Controller of the Navy), and Admiral Sir Frederick Richards, who also were members of the Board of Admiralty; by Captain Hopkins (Director of Naval Ordnance), and by several members of the constructive and engineering staff of the Admiralty. Since this period numerous vessels of the class have been added to our own and other navies, and great advances have been made, but none comparable with that now achieved in the Italian cruiser *Piemonte*, also constructed by Sir W. G. Armstrong, Mitchell & Co. This vessel was described a few weeks back at the meetings of the Institution of Naval Architects by her designer, Mr. P. Watts, and the bulk of his paper and the discussion which took place thereon were published in our issue of April 26. When this paper was read, however, the steam trials had not been completed, and the results given were based upon a single preliminary run, at which the full power of

the machinery had not been developed. The official trials have now been completed, and the results are before us. During a natural draught trial of four hours' duration, a mean speed of 20.4 knots was attained with about 7,000 indicated horse power; and during a forced draught trial of one and one-half hours' duration, a measured mile speed of 22.3 knots was attained with a mean power of 12,700 horses, the maximum power which was maintained for a considerable time exceeding 13,000 horse power. The displacement of this vessel is only 2,500 tons, yet she carries six 6 in. quick-firing guns, six  $4\frac{1}{4}$  in. quick-firing guns, and a large number of smaller guns. She is protected by a strong armor deck with sloping sides, and she has attained a greater speed than that contemplated in the *Blenheim*.

At the present moment she is by a great deal the fastest cruiser afloat. She is, we believe, two knots faster than any of the cruisers built by our own Admiralty. Moreover, she is specially designed for steaming with open stokeholds, and she can attain a speed of  $20\frac{1}{2}$  knots with natural draught, or with a pressure in the stokeholds not exceeding half an inch of water, the pressure allowed by the Admiralty for developing the draught when the wind is not sufficiently favorable for the purpose;  $20\frac{1}{2}$  knots may be regarded as her ocean-going speed.

The great importance of this high performance with natural draught will be understood by those conversant with the effect of forced draught upon ordinary marine boilers, and will be fully appreciated when it is remembered that the Admiralty in a recently issued circular directs that forced draught appliances are not to be used at their full power, or, in other words, with above  $\frac{1}{2}$  inch of pressure, except in circumstances of emergency, and then only for short periods when the maintenance of the highest possible speed for three or four hours may be of great advantage. The *Piemonte* can steam continuously across the ocean a knot faster than any of the Admiralty cruisers can steam with forced draught, which they can only maintain on an emergency for three or four hours.

The armor deck of the *Piemonte* has sloping sides 3 inches thick, as in the Admiralty cruisers; upon these coal can be carried, and in this condition it is claimed that the deck is proof against the attack of modern shell guns up to guns of 6 inches caliber.

This ship is the first to be fitted with new quick-firing guns. Speaking of her armament on a recent occasion, Lord Armstrong said, "She will be capable of discharging against an adversary, in a given time, twice the weight of shot and shell that could be fired by the largest war vessel now afloat, not excluding the leviathan battle ships of five or six times her size, which could ill withstand the torrent of shell which the *Piemonte* could pour into the large unarmored portions of their structure."

The machinery of the *Piemonte* is wholly below the water line; it has been constructed by Messrs. Humphrys, Tennant, and Co., Deptford. There are two sets of vertical triple expansion engines, in each of which there are two low pressure cylinders, so that there are in each four cranks operated upon. Ample distilling apparatus is provided for making fresh water for the boilers. At full speed with forced draught, although the enormous power of 13,000 horses is developed, the vibration at the extreme after end of the ship never exceeds 12 inches in amplitude.

The vessel can carry 600 tons of coal, which will enable her to steam at full speed a distance of 1,950 knots, but she will be able to maintain a cruising speed of from 10 to 12 knots for from 50 to 50 days, during which she could cover a distance of 13,500 knots.

Special arrangements have been made for securing good turning power in the ship, a large balance rudder is provided, and much of the after deadwood is removed, and at the trials made it was shown that the ship could maneuver exceedingly well, completing a circle of 508 yards in 3 minutes 24 seconds.

Lord Armstrong, probably the strongest advocate for the construction of this type of vessel, has enumerated as their chief features, "Great speed and nimbleness of movement combined with great offensive power," and "little or no side armor, but otherwise constructed to minimize the effect of projectiles," and in the *Piemonte* all of these features have been secured in the very highest degree, and there can be no question that for her size she is the most formidable cruiser afloat. We are very glad she has fallen into the hands of such a friendly government as that of Italy.—*Engineering*.

**Does Heating Milk Affect the Quality or Quantity of Butter?**

Experimental studies of this question at Cornell University show the following results: First, that there is a loss of butter when the milk is allowed to cool much below the normal heat of the cow before being put in the creamer; second, that while there may not be any very great increase of butter when the milk is heated, there is no risk of injuring the quality of the butter by incorporating an excess of casein, even when the milk is heated as high as 135 degrees.



## Correspondence.

## A Correction as to Earth Theories.

To the Editor of the Scientific American:

If the reviewer who, on page 344 of the issue of June 1, 1889, of the SCIENTIFIC AMERICAN, noticed an article by Prof. Joseph F. James (not Jones), will again read the article he noticed, he will find that the Professor does not assume "the earth to be a hollow sphere" and so on, but that he is quoting from some one else who does the assuming. The Professor does not desire to be credited with any such sort of scientific knowledge. He leaves that to others who speculate upon the subject. Suffice it to say, he does not believe in the crude theories he has noticed.

JOSEPH F. JAMES.

Washington, D. C.

## Novel Experiments on Light and Electricity.

The following is from the London *Electrician*: "An experiment described by M. J. Borgman has an important bearing upon the explanation of the remarkable discovery of M. Hallwachs, in which a beam of light seems to act as a conductor for an electric current. The latter experiment consisted in placing a piece of metallic gauze parallel with, but insulated from, a second sheet of metal. The first is connected with the positive, the second with the negative, pole of a battery, and in one of the leads a delicate galvanometer is placed. If, now, a beam of light be made to pass through the gauze, and to fall on the plate behind, a current is set up in the circuit, and continues to flow as long as the illumination is maintained. It has, moreover, been shown that the action is due to the ultra-violet waves. Now, M. Borgman wanted to ascertain whether or not the effect was instantaneous; that is to say, whether the commencement and the cessation of the current was or was not simultaneous with that of the illumination. M. Borgman probably reasoned that, if the beam acted in some sense as a conductor of the current, the effect must be instantaneous; while, if the phenomenon resulted from some secondary action, it would probably go on increasing up to a certain point with the duration of the illumination, and it would also probably continue for a time after the light had been cut off. His method of making the test was equally simple and ingenious. The light was interrupted at rapid intervals by means of a rotating disk with holes or slits, and he placed a telephone in circuit with the battery. It is, then, obvious that, if the effect is instantaneous, the telephone will produce a note corresponding in pitch to the velocity of the disk; if otherwise, there will be silence. There was silence. A make and break in any other part of the circuit could be heard, but not in the beam of light: hence we must seek for some secondary action on the surface of the plates to explain M. Hallwachs's experiments."

## Lead Poisoning.

At a meeting of the Practitioners' Society of New York, Dr. Kinnicutt, the president, reported two cases of lead poisoning occurring from an unusual source. The first patient was admitted to St. Luke's Hospital, suffering from lead colic and "wrist-drop." He had been employed as a florist; and on investigation by Dr. Vaughan, the house physician, it was found that he had been in the habit of biting off the ends of the tinfoil used as wrappers for hand bouquets. The tinfoil used for this purpose contained as much as 80 per cent of lead. There was no history of other sources of lead poisoning. The second patient was admitted to the hospital, suffering from lead colic, and presenting a typical blue gum line. He had been in the habit, for several weeks, of drinking beer from bottles which, he said, were cleaned by his employer with lead shot. Dr. R. F. Weir recalled the fact that several cases of lead poisoning, some years ago, had been traced to the use of a popular brand of chewing tobacco which was wrapped in tinfoil. Dr. Dana referred to some cases of poisoning which had been traced to the consumption of certain beverages coming in bottles with so-called patent stoppers. He said that he had recently had two Chinese patients in the hospital service, both of whom were suffering from lead poisoning. He was unable to trace the source of the poisoning.—*Science*.

## New Steel Process.

The Redemann-Tilford steel process is understood to consist of a bath with glycerine as the basis. This bath changes the whole structure of the metal submitted to it, and increases its ductile and tensile strength far beyond any record that has yet been established by either private or governmental test.

When it is stated that the very finest and strongest grade of steel, much better than any now in use, can be made by this process at little more than the cost of crude Bessemer steel, the value of the discovery may be understood. Thus far, in making experiments, every character of tool and steel goods has been worked with, and the process has been successfully used upon all.—*Manufacturers' Record*.

## Clark University, Worcester, Mass.

This new and magnificent institution of learning will open its doors and begin its grand career of usefulness in October next. Applications of students for entrance are now being received.

Clark University was founded by the munificence of a native of Worcester County, Jonas G. Clark, Esq., whose plans, conceived more than twenty years ago, have gradually grown with his fortune. His affairs have been so arranged as to allow long intervals for travel and study. During eight years thus spent, the leading foreign institutions of learning, old and new, were visited and their records gathered and read. These studies centered about the means by which the highest culture of one generation is best transmitted to the ablest youths of the next, and especially about the external conditions most favorable for increasing the sum of human knowledge. To the improvement of these means and the enlargement of these conditions, the new university will be devoted. His pecuniary endowments to the institution rise to several millions of dollars.

It is the strong and express desire of the founder that the highest possible academic standards be here forever maintained; that special opportunities and inducements be offered to research; that to this end the instructors be not overburdened with teaching or examinations; that all available experience, both of older countries and our own, be freely utilized, and that new measures, and even innovations, if really helpful to the highest needs of modern science and culture, be no less freely adopted; in fine, that the great opportunities of a new foundation in this land and age be diligently explored and improved.

Prof. G. Stanley Hall, formerly of Johns Hopkins University, is the president. He is one of the ablest of scientific men.

The corps of professors and instructors is large, and embraces many prominent men of talent of the highest order. Every department will be made as complete and effective as possible.

The organization of all departments will be gradual, and the foundation period of the university will cover some years.

Apparatus is being extensively ordered of the best makers in this country and in Europe, chiefly from those who devote themselves to the special class of apparatus in which they excel.

The university is situated in Worcester, the third city of New England in size, with 80,000 inhabitants. It is one hour westward from Boston by rail, and five hours from New York City. Central among the best New England colleges, the location is most favorably chosen for attempting the next step in the higher university development of the country.

Worcester is also the seat of the following institutions of an educational character:

The American Antiquarian Society, an institution of national character and repute, organized in 1812, with a library of 85,000 volumes, possessing funds and collections, and issuing publications of its own.

The Worcester Free Public Library, containing about 75,000 volumes and receiving about 250 periodicals.

The Worcester Polytechnic Institute, incorporated in 1865, with three large and well appointed buildings, fifteen instructors, and a three years' course mainly in the sciences and their application to the practical arts.

The Worcester Lyceum and Natural History Association, incorporated in 1866, and containing extensive local collections.

The College of the Holy Cross, a Catholic institution of high grade, incorporated in 1865, and with a corps of fifteen instructors.

In addition to these may be mentioned a law library of 12,000 volumes; a medical library of 8,000 volumes; a State Normal School with a two years' course, eight instructors, and about two hundred students; one high school; the Highland Military Academy, founded in 1858, with seven instructors; the Worcester Academy, a private institution, founded in 1874; and several other libraries, societies, and educational institutions.

The university is located in the western part of the city, about a mile from the central station. The grounds are over nine acres in extent.

A plain, substantial, and well-appointed central building, 204 by 114 feet, four stories high, and with superior facilities for heating, lighting, and ventilation, has been constructed of brick and granite, and finished throughout in oak.

A chemical laboratory, designed after consulting many experts and plans of recent European buildings, and containing about fifty rooms, is nearly completed.

The foundations of a still larger department building are laid.

The work of instruction will begin on Wednesday, October 2, 1889, in the following departments: Physics, under direction of Prof. Albert A. Michelson; Biology, Dr. Warren P. Lombard; Psychology, President Hall; Chemistry and Mathematics, professors not yet announced.

The charge for tuition, giving all the privileges of the university, but not covering laboratory fees, will be \$200 per annum.

## Felling Trees by Electricity.

Hitherto machines for felling trees have been driven by steam power, but this is often inconvenient, especially in thick woods, because the heavy machinery, including a boiler, must be placed near the tree to be cut. These machines, therefore, can only be used on the borders of forests or in open spaces readily reached by good roads. The London *Times*, however, reports that electric power has been adopted in the Galician forests. Usually in such machines the trunk is sawn, but in this case it is drilled with a series of holes close together. When the wood is of a soft nature, the drill has a sweeping motion, and cuts into the trunk by means of cutting edges on its sides. The drill is actuated by an electric motor mounted on a carriage, which is comparatively light and which can be brought up close to the tree and fastened to it. The motor is capable of turning around its vertical axis, and the drill is geared to it in such a manner that it can turn through an arc of a circle and make a sweeping cut into the trunk. The first cut made, the drill is advanced a few inches and another section of the wood is removed in the same way, until the trunk is half severed. It is then clamped, to keep the cut from closing, and the operation continued until it would be unsafe to go on. The remainder is finished by a hand saw or an ax. The current is conveyed to the motor by insulated wires brought through the forest from a generator placed at some convenient site, which may be at a distance from the scene of operations. The generator may be driven by steam or water power, and does not need to be transported from place to place.

## Effect of Light on Magnetism.

At a recent meeting of the London Physical Society, Mr. Shelford Bidwell showed a lecture experiment illustrating the effect of heat on the magnetic susceptibility of nickel and an experiment showing an effect of light on magnetism. In the first experiment a piece of nickel was attached to one side of a copper pendulum bob, which was held out of the vertical by bringing the nickel in contact with a fixed magnet. On placing a spirit lamp flame below the nickel, the bob was, after a short time, released, and oscillated until the nickel had cooled, when it was again attracted and the operation repeated itself. The second experiment had been recently shown before the Royal Society. One end of an iron bar, which had been magnetized and then demagnetized, was placed near a magnetometer needle. On directing a beam of light on the bar an immediate deflection of the needle resulted, and on cutting off the light, the needle promptly returned to near its initial position. The direction of magnetization induced by the light is the same as the previous magnetization, and the bar seems to be in an unstable magnetic state. That the effect is due to light and not heat, the author thinks is rendered probable by the suddenness of the action. The president said he had tried the experiment himself and failed to get any effect, but after seeing the arrangement of apparatus used, he believed his non-success due to the comparatively great distance between his bar and needle. Mr. C. Richardson asked if the results were different for different colored rays, and Prof. S. P. Thompson inquired whether the magnitude of the effect varied with the intensity of illumination as in selenium, and also if any change was produced by altering the direction of vibration of the incident light. Mr. G. M. Whipple wished to know whether any difference was produced by blackening the bars, and as bearing somewhat on the same subject mentioned an induction magnetometer in which an iron bar used was demagnetized by plunging in hot water. The results obtained were very irregular after the first magnetization, and this may have been due to the instability shown to exist by Mr. Bidwell's experiment. In reply, Mr. Bidwell said red light produces most effect, and blackening the bar makes the action much slower. As regards selenium, the character of the effect is similar, but he believes the causes to be different. Polarized light produces no change. In answer to Prof. Herschel, he said that any part of the bar is sensitive to light, and showed that illuminating both sides of the bar increased the effect.

## Success of the British Canadian Steamers.

The Canadian Pacific line of steamers from Vancouver to Japan have now been running for a little over a year, and are completely cutting out the Pacific mail steamers under the United States flag which sail from San Francisco. The rates of freight are much the same, yet in the past tea season the Canadian Pacific steamers carried 5,357,944 pounds of Japan tea, against only 735,265 pounds carried by their American rivals, and the curious circumstance is that more than nine-tenths of this tea is consumed in the United States. Not in tea only, but in all other goods, is the preference given to the Canadian line, which now carries a large part of the transcontinental traffic, as well as that destined for the United States. The journey to Vancouver is shorter, but this alone would not account for this wholesale transfer of trade.—*Canadian Manufacturer*.


# COLLAPSE OF THE SOUTH FORK DAM AND DESTRUCTION OF JOHNSTOWN.

(Continued from first page.)

twenty feet wide, and rock was spread over both faces. The material of the work was clay or silt, apparently

spillway, but which is located on the other end of the dam from that shown in the same view.

The following details of the overflow and collapse of the dam, as obtained at the spot by the representative of the SCIENTIFIC AMERICAN from a witness of the



THE STONE BRIDGE AND THE BLOCKADE ABOVE IT.


most excellent material, if properly used. It was of such nature as to form a thoroughly impervious barrier though, unfortunately, very easily cut away on its exterior surface. In the core of the structure a row of sheet piling could be seen which had been used in the original construction, but which added very little to its strength. The material exhibited marks of stratification, showing what miners would call "stopes" or steps upon the sides of the crevasse. At the eastern end the regular spillway or overflow was placed. This is a sluice or canal cut through the rock, about forty feet wide, with its bottom eight or ten feet below the top of the dam. It was crossed by two bridges, and some idea of its size can be derived from the evident length of the one shown in perspective. A fish screen, to prevent the fish from escaping, crossed the channel, but as it was only three feet high it could not have greatly impeded the water. It is not now in place, being broken and destroyed. It is quite possible that it was carried away before the overflow began. Five lines of cast iron pipe, about twenty inches in diameter, ran through the base of the dam, terminating in masonry tunnels reaching well outside of the base. These were permanently closed. The ruin of the gate house for these pipes is shown in one of the cuts. On top of the gate house, at the foot of the inner slope of the dam, as shown in one of our views, there was originally a wooden tower, containing appliances for opening and closing the gates. This tower was carried to only a few feet above the water level, and was reached only by boat. After a former break in the dam, some years ago, this tower was burned, and when the dam was rebuilt this central outlet was permanently closed. Some of the charred timbers remaining from this tower are still to be seen around what remains of the old gate house. The same illustration gives a sectional view showing the comparative area of the regular

whole occurrence, coincide with Mr. Parke's account. The water had been rising rapidly, and at midday was within a foot of the top. The spillway was discharging water to its utmost capacity, producing a perfect cataract. A little after one o'clock the top was reached, and before long the water began to flow across the roadway at the ends of the dam. The streams, growing wider, worked their way toward the center, and eventually poured over that portion as well. Then the destruction began. The water began to cut into the soft material, dredging away the unsupported clay, and every instant increasing the opening. In about an hour and a half the reservoir was empty, and a crevasse 350 feet wide at the top was formed, through whose bottom the stream flowed.


Whatever may be the finally accepted view as to the principal cause of the great disaster, it is evident that the dam itself was abundantly strong enough to hold back the water contained in the reservoir until a breach had been made at the top by the water flowing over its face. To prevent this the spillway at the side had been constructed. This spillway was made through solid rock, and had afforded an ample outlet for all surplus water, without danger to the dam, for a period of eight years. That this spillway should have been made

The water from the lake rushed down the South Fork, carrying with it much of the debris of the dam. At the village of South Fork it turned with the stream, and, after inundating the village, by a return wave carried much of it away. With a continually increasing burden of wreckage it went down the Little Conemaugh toward Johnstown. At Conemaugh it struck the Pennsylvania railroad's round house. It destroyed it and scattered the engines in all directions. Near this point it also carried away the day express which was standing there unable to proceed or retreat on account of the condition of the tracks. A number of the engines from the round house were carried into the bed of the South Fork and left there covered with rock and material of all kinds. The channel was completely filled, and at present the stream goes through a new channel several hundred feet distant. Our cut gives the scene at this point. Houses in Conemaugh that formerly were back from the stream and cut off from sight of it by other houses, now stand upon the brink of the new channel. How the question of title to land will ever be settled cannot be seen. The diversion of the stream is undoubtedly a permanent change, and now it runs over what were once building lots in the town of Conemaugh.


The inhabitants of the settlements near the dam had obeyed Mr. Parke's warnings, and the loss of life there was slight. But Johnstown was already flooded, and the people, apparently too familiar with floods, and regarding them only as discomforts, paid no regard to the messages from the lake. The torrent poured down upon them through the Little Conemaugh. At Johnstown this stream bends at almost a right angle and is joined by the waters of Stony Creek. This is shown very clearly in the bird's-eye view of the region. The flood came in with irresistible power and did not follow the curve, but drove across the bend of the Little Conemaugh, and rushed over the flats through the heart of



CROSS SECTION OF THE DAM.



MASONRY WORK AT THE OUTLET BENEATH THE DAM.



SOUTH FORK LAKE BEFORE THE DESTRUCTION OF THE DAM.

still deeper is now evident enough, and had this been done, and the water thus prevented from pouring over the face of the dam, all positive evidence is wanting to prove the insufficiency of the dam to hold back the water of the reservoir. The dam was not undermined, but was cut away from the top downward, as if by a hydraulic dredging machine or mining plant.

Johnstown until it met the swollen waters of Stony Creek. Here it went in two directions, backing up the creek as well as rushing down it. Just below the junction of the two streams is the stone railroad bridge. Up to this point the water had carried away every bridge it encountered. But the stone structure was too strong. It stood the strain and at once the immense mass of debris piled up against it. The water was thus held back in Johnstown as if in a shallow basin. It formed a gigantic whirlpool and began circling around the valley, completing the work of destruction. On the first overflow it had swept through the city and carried a mass of houses and wreckage into Kernville. When all was over, Kernville was left full of the Johnstown buildings, and to-day it may be said that every lot in Kernville has one or more houses on it that once stood on the opposite side of Stony Creek. In the region of the center of the whirlpool, some structures were left nearly intact.

The water in its passage from the lake to Johnstown descended about 250 feet. The theoretical velocity due to this descent would be about 127 feet per second, or between 86 and 87 miles an hour. According to the best accounts that we have, from 15 to 17 minutes was occu-



pied in the passage to Johnstown, a distance of about 12 miles. Thus the average velocity could not have been far short of 50 miles an hour. The impetus of such a mass of water was irresistible. As the flood burst through the dam, it cut trees away as if they were stalks of mullein.

The region surrounding Johnstown has a large lumber interest, and many saw logs found their way into the torrent, principally coming from the country near Stony Creek. These added to the strength of the blockade at the bridge. For several days a number of stationary steam engines have been at work dragging the larger pieces of wood and wreckage out of the dam, in order to give a clear passage to the water and to remove the remains of human beings and animals that, decaying, may yet give rise to sickness.

The most widespread movement for relief has naturally taken place. Contributions of all kinds as well as money have been liberally donated. After various vicissitudes in the way of government, wherein the military and civic authorities tended to come in conflict with each other, the region has been placed under martial law, with Adjutant-General Hastings in command.

From West Point and Willets Point pontoon equipments were dispatched, and temporary bridges of this description were erected where required. Over one place a suspension bridge has been built. A quantity of tents have been pitched, and many of the features of army life are to be seen. A view is given illustrating these aspects of the scene, and showing the Willets Point pontoon bridge. The loss of life is quite uncertain. A bureau of registration has been established for the survivors, and a total of about 16,000 individuals are represented on its pages. About 1,900 bodies, over half of which were identified, have been recovered. It is proposed to compare the statistics collected with the most recently compiled directory of Johnstown, and thus arrive at a better estimate of the loss.

As stated in our previous issue, the damage to life and property by the storm was not confined to the Conemaugh region. On the other slope of the Allegheny mountains floods and inundations occurred, sweeping millions of feet of logs down to the Chesapeake and out to sea. As a bounty is allowed for the saving of such logs, a considerable portion will be secured, but many are now afloat far out on the ocean. A captain of a schooner describes being caught among them, and gives a graphic account of the trouble he had in escaping.


#### Ocean Currents.

At the recent conversazione of the Royal Society a model illustrating the formation of ocean currents was exhibited by Mr. A. W. Clayden. This is practically a map of the Atlantic in which the land surfaces are raised about half an inch above the portions occupied by the sea. The continents and larger islands are made of wood cut into the required shape, while the smaller islands are represented by pins or small pieces of sheet metal driven into the board which forms the basis of the whole.

This raised map forms the bottom of a shallow tray, which can be filled with water up to the level of the land surfaces, thereby obtaining a map (on Mercator's projection) in which the seas are represented by the surface of water. Underneath the tray a wind chest is fixed, and a number of tubes are brought up from it through the continents, and bent over so that the jets of air delivered from them may impinge upon the water. These jets are so arranged as to approximately reproduce on a small scale the actual circulation of the atmosphere as laid down on a chart of the prevalent winds for the year. Care is taken to have as few tubes as possible, and they are so placed as to hide the least possible amount of the sea. The strong and persistent trades are simulated by bringing the openings of the tubes near to the surface of the water,

while the fitful and uncertain winds of northern latitudes are imitated by allowing the jet to be considerably dispersed before coming into contact with the water. A foot blower is attached to supply the wind, and any movement of the water is rendered visible by scattering over it some lycopodium powder.

All the principal currents of the North Atlantic are shown, including the return current between the great equatorial currents, and the northward stream



TEMPORARY BRIDGES OVER STONY CREEK.

along the west coast of Greenland. If a narrow opening is made in the Isthmus of Panama all that happens is that some of the return stream round the Mosquito Bay and Gulf of Darien flows into the Pacific, leaving the North Atlantic practically unaffected. But if a large part of Central America is removed, almost the whole of the tropical water passes through the opening, and the currents from Baffin's Bay and the Arctic Ocean are drawn down to the Azores.

There is an absence of evident connection between the slack water close to the New England coasts and the Labrador current, but the apparatus does not attempt to imitate differences of temperature or differ-

#### Communication of Infection.

From the number of cases reported of infectious diseases that have been communicated through articles that have been in the possession of those afflicted with such diseases, it would seem that greater attention should be given this matter. The virulence of many disease germs has been shown, says the *Sanitary News*, to be of long life, capable of being transmitted through many years. Cases of scarlet fever, diphtheria, and typhoid fever have been reported in which the infection was communicated by articles that had been possessed by the sick years before.

In cases of small pox and yellow fever, infection by this means is considered well enough founded and dangerous enough to make the destruction of clothing and all articles exposed to infection imperative by a general law of health departments. If such articles are not burned, they must be subjected to disinfection by steam at a high temperature.

Our public and circulating libraries, "second-hand" book, clothing, furniture, and other stores, are all means by which disease germs could be communicated. Dealing in "second-hand" goods has grown to such an extent that almost all communities have representatives in their midst. Goods may be on the tables of the "second-hand" dealer or broker which could have hung in the room of one afflicted with some infectious disease for weeks, and no one who may want to purchase, or even the dealer himself, know of it. Or there may be the furniture, or even the bed and bedding on which the patient lay.


Probably the most danger lies in books. With most patients there is a time in their sickness when they want books with which to pass the hours of convalescence. The home library seldom is sufficient, and the public or circulating library is resorted to. The book goes from the patient's into another's hands, bearing all the seeds of disease of which it is capable. Either there is danger of communicating disease in this way, or the germ theory is a failure.

This matter has been deemed of such importance that in many European countries extensive investigations are being made regarding the infectiousness of books handled by the sick. The investigation should extend to all "second-hand" goods, and be conducted with great care and minuteness. In commenting on this subject, the editor of the *Christiania* (Norway) *Sanitary Journal* gives the following personal experience, which is but one of similar cases reported:

In 1846 an eight-year brother of my wife was taken down with scarlet fever and died. During his illness he frequently amused himself by looking over a large picture book. This, together with several other of his useful playthings, was packed away in a chest after his death. Twenty-six years afterward, in 1872, a sister-in-law of mine journeyed across the channel to England, where I was then residing, and with her came the chest and the picture book. On the second day the chest was opened and the book presented to my two-year old son. Within the next two weeks the little fellow was taken down with scarlet fever. The doctors who were called in consultation wondered how the disease was contracted, as there had been no scarlet fever in the town for years. The circumstances of the book were called to mind, and the indications were clearly that the twenty-six year old book had retained the poison and communicated it to the child.

Had not this book been mentioned and its history given, here would have been a case of "spontaneous"

scarlet fever. Phthisis is said to be communicated by sweepings from carpets in the rooms occupied by such patients, yet "second-hand" carpets are not only placed on sale, but hung out of store windows and displayed on the sidewalks, and no one knows how contaminated they may be from the expectorations of the consumptive.



1. The Reservoir and Dam. 2. Conemaugh or Franklinboro. 3. East Conemaugh and buried locomotives. 4. Chemical works. 5. Grist mill. 6. German Catholic Church. 7. B. & O. R.R. Depot. 8. Methodist Church. 9. Cambria Co.'s Stores. 10. School House. 11. Cambria Iron Works. 12. West Point Pontoon. 13. Temporary B. & O. R.R. Depot. 14. Willets Point Pontoon. 15. School House Morgue. 16. Lutheran Church. 17. Baptist Church.

#### BIRD'S-EYE VIEW OF CONEMAUGH VALLEY AND JOHNSTOWN.

ences of rotational velocity. Hence any effect due to either of those causes must necessarily be absent. All that is attempted is to demonstrate the connection between the prevalent winds and general oceanic circulation, by showing that nearly all the movements of the water are determined by the direction of the winds and the contours of the coasts.

## PHOTOGRAPHIC NOTES.

**Negatives Developed during Exposure.**—M. Tondeur has again shown negatives developed during the camera exposure. He contents himself, in order to obtain this result, with immersing the plate in hydroquinone developer and draining it, then he exposes it in the camera. If the time of exposure is sufficiently long, the development is completed simultaneously; if, on the other hand, the negative has been taken instantaneously, it must be left the necessary time for development. What escapes us for the moment is the practical application to be made of this method of action. However this may be, it is well to take notice of everything fresh, the question of application being one ulterior to that of the possibilities that may be in store.—*Leon Vidal, in the Photo. News.*

**Apparatus for Automatic Photography.**—Mr. Enjalbert, who has already furnished proofs of his ingenuity in contrivances, has worked out a very curious automatic apparatus, in which all the operations are mechanically effected by an electromotive engine. This apparatus is prepared for the Paris exhibition, where it will be seen in work; but we have been favored with an opportunity for inspecting it and seeing it in action. It is certainly a marvel of ingenuity. The apparatus is started by placing a 10 centime piece in it, and the subject having placed himself in the prescribed place, a ferrotype plate is coated with collodion, bathed, and adjusted to the focus of the lens, when the exposure is made. It is then led into a developing solution, fixed, and washed, and in a very short space of time the portrait comes out of an opening in the machine, accompanied by a small frame in which to place it. The ingenuity required to work out all these operations automatically is truly astonishing.

**Photographing on Wood.**—The following method, taken from the *Revue Photographique* (translated in the *Photographisches Archiv*), can be recommended as a good one: 8 grammes of gelatine are soaked in 500 c. c. of water, dissolved on a water bath, and 8 grammes of white soap are added to it gradually, well stirring all the time. The mixture is filtered through muslin, a little zinc white added to it, and then rubbed well into the wood block and allowed to dry. The film should be as thin and even as possible. When dried, the following solution is applied to the wood by the aid of a broad brush:

Albumen.....	30 grammes.
Chloride of ammonia.....	1.2 "
Citric acid.....	0.2 "
Water.....	24 c. c.

The albumen is beaten up to a froth, allowed to settle, and then is added the water, the chloride of ammonia, and the citric acid, exactly in order given here. When dry the film should be sensitized by pouring on the following solution, spreading it with a glass rod:

Nitrate of silver.....	3.2 grammes.
Water.....	31 c. c.

The excess of this sensitizing solution is poured off and allowed to dry again. Printing is effected as usual in the printing frame. It is not necessary to overprint. When sufficiently printed, the wood block is held with its surface for three minutes in a diluted solution of common salt. The print will become only slightly paler in it. Wash and fix for four or five minutes in a concentrated hypo. solution, wash again for ten minutes in running water, and allow to dry.

**Photography Applied to the Prediction of the Weather.**—With regard to the accident which has occurred to the German navy at Apia, it might be advisable to refer once more to the theory of Dr. Zenger, of Prague, who suggested, as it will be remembered, to make use of photography for the prediction of the weather. According to the doctor, photographs of the sun taken on orthochromatic plates offer a most infallible means to indicate with almost absolute certainty the approaching atmospheric and subterranean disturbances at least twenty-four hours before their setting in. In these photographs zones are often to be seen around the sun's disk—i. e., rings of circular or elliptical form, of white or grayish color—and if these zones appear of very large diameter, and of unusual heaviness, this indicates that violent storms, thunderstorms, or magnetical disturbances will soon set in at the place of observation. At every ship's station should therefore be established a small photographic laboratory, in which photographs of the sun could be taken as often as possible. A much more reliable prediction of the weather would be afforded by this means than by the aid of the barometer now generally in use for this purpose, and precautions could therefore be taken in good time.—*H. E. Gunther, in Photo. News.*

THE English are contemplating an idea to lay down a postal tube between Dover and Calais. The plan is to suspend two tubes of about a yard each in diameter by means of steel cables across the channel, forty yards above the level of the sea. The steel cables will be fixed to pillars at distances of about 800 yards, and in each tube a little railway will run with cars capable of carrying 450 pounds in weight. No parcel of greater weight than this will be taken, and the cost is estimated at the modest figure of \$5,000,000.

## About Melons.

Years ago it was a common practice to plant melons, literally, in "hills" raised above the surface of the ground, and some still think such a practice necessary. When the seed is sown early there may be some advantage in this, since the elevation will be warmer than the flat surface. But, as a rule, in soil best suited for melons—a warm, sandy loam—a more thrifty growth and more prolonged health of the vine can be secured by making the hills really hollows. Nothing so promotes the growth of a melon vine as the drawing of fresh earth to the stem, and a vine planted a few inches lower than the general surface of the soil, by a gradual drawing-in of the soil by the time cultivation ceases can be on quite a ridge, and thus get the advantage of the hill with the further advantage of having its roots in moister and cooler soil than would have been possible if planted on a ridge. These remarks will apply equally well to watermelons as to muskmelons.

In growing melons for home use quality is the first consideration. Of late years the effort among seedsmen has been to produce a watermelon with a tough rind, adapted to the long shipment from the South. This has been obtained at the expense of quality. In our home garden it is of no sort of advantage to raise a watermelon which will support a weight of half a ton, as some are said to do. Neither do we care for its being "iron clad" or "copper fastened," unless the inside is well worthy of such protection. The newer sorts of watermelons, while they have been improved for the purposes of the shipper, have not been of the average quality of some of the older sorts. We have found none superior for this region to the "Gypsy" and the "Mountain Sweet." The "Volga" is said to be small and of high quality, but we are growing it for the first time this year and cannot give an opinion upon it. In muskmelons it is also a good rule to select varieties, not by size and looks, but by their quality for the table. In muskmelons size is often attained at the expense of quality. Many contrivances have been proposed for protecting young melon seedlings from the attacks of the striped bugs, which devour them when in the seed leaf, but most of them are very troublesome. For many years I have used a little raw bone-flour, dusted over the young plants as soon as they are fairly up. If beetles are there they leave at once, and the plants are benefited by the application.

Early fruitfulness is promoted by nipping off the tips of the vines when about three feet long.—*W. F. Massey, Garden and Forest.*

## Government Schools in China.

In 1885, after peace had been declared between France and China, the viceroy, Li Hung Chang, obtained the imperial sanction for opening military and naval schools at Tien-Tsin, where Chinese pupils could receive instruction in western sciences. The military school has been in operation five years, has 150 pupils, and one class has already graduated. It has four German professors, and the instruction is entirely in the German and Chinese languages.

The naval school is divided into two departments—the executive, for the training of naval officers, and the engineering, for the training of engineers. The number of pupils is 120, selected from the different provinces of the empire, and the length of the course is five years. The director of studies is Mr. Yen Tsung Kwang, who is assisted by three English professors, two of whom belong to the English navy. Mr. Yen Tsung Kwang is a graduate of the foreign school at Foo-Chow, who, after seeing service afloat, was sent to the royal naval school at Greenwich, where he graduated with high honors. The remarkable proficiency of the pupils of the naval school, as shown at the public examinations, reflects the highest credit upon Mr. Yen Tsung Kwang and his associates. These examinations are conducted much in the same way as at West Point and Annapolis, and the subjects embrace all the higher branches of mathematics, the difficult problems of which the Chinese mind is said to master with extraordinary facility.

A school for instruction in telegraphy was organized in 1880, and at present has 48 pupils. The instructors in this school are Danes, but the instruction is given in the English language.

A local medical school, with a hospital attached, was founded some years ago by the viceroy. This school is now about to be reorganized with an eminent foreign doctor at its head, the object being to qualify young men for the medical profession and attach them to the army and navy, as well as other branches of the public service.

In addition to the schools already mentioned, an Anglo-Chinese college will be opened early in the year 1889. The building for this college was commenced in 1887 and is now nearly completed. It is a fine Gothic structure, situated on the left bank of the Peiho, and has accommodations for 300 students. The organization of this college is not yet complete, but it is understood that the curriculum will be more extended than at any of the other schools, and will include a general course of study in the English language and literature, as well as in mathematics and the sciences. It is

reported that Mr. C. D. Tenney, an American, now the private tutor of the viceroy's children, will be placed at the head of this college.

When it is considered that hitherto the officers in the Chinese army and navy below the rank of general and admiral have been taken from the uneducated classes, and have obtained their commissions often by purchase, and that both branches of this service have been without a medical staff, the importance of the educational establishments at Tien-Tsin, promoted and fostered by the viceroy, cannot be overestimated.—*Report of Consul Smithers.*

## Purdue University.

Purdue University, at Lafayette, Ind., is a State institution. It is supported by legislative appropriations and by the proceeds of an endowment fund granted by the general government. It derives its name through legislative enactment from John Purdue, who gave to the State for the use of the institution \$150,000. It has a permanent endowment fund to the amount of \$340,000, and other non-productive property in buildings, lands, and equipment to the value of \$330,000.

It has one hundred and eighty acres of land in its campus and farm, fifteen buildings, well equipped laboratories, shops, museums, library, and reading rooms.

Its purpose is to afford young men and women of Indiana an opportunity to acquire a good collegiate education in mathematics, science, literature, and art, and at the same time to secure instruction and practice in such lines of work as will fit them to engage in the practical industries of life. The instruction is both theoretical and practical. The usual methods of text book study, recitation, and lecture are employed, but the student is required to put into practice as far as possible the instruction which he receives. He, for example, not only receives instruction in regard to the theory and principles of drawing, pattern making, and machine construction, but he is required to make working drawings himself, to construct patterns, to make the castings in the foundry, to finish and set up the machine, and to operate it when it is completed. This combination of the theoretical and the practical characterizes the institution.

Being a State institution, the instruction in Purdue University is free to all residents of Indiana of suitable age and acquirements. Small laboratory, library, and incidental fees only are charged.

The institution embraces seven special schools and a preparatory department, as follows: A school of agriculture, horticulture, and veterinary science; a school of mechanical engineering; a school of civil engineering; a school of electrical engineering; a school of science; a school of industrial art; a school of pharmacy.

## How to Increase your Wages.

Every thinker knows that the man who would succeed must do more work than he gets paid for, in every profession and trade. We take it for granted that the man who will do only \$20 worth of work a week because his salary is but \$20 will never get more than \$20 a week, for the simple reason that he has never shown his employer that he is worth more. We figure it that an employe who means to succeed has to do from 10 to 20 per cent more work than he gets actual pay for. This he has to do until he reaches a certain point, and having reached that point he will find that by as much as his income has increased, by so much has the demand for amount and intensity of his labor diminished. To put this theory into figures, we will say that a boy receiving \$3 a week should do \$4 worth of work; the boy receiving \$5 a week should do \$7 worth of work; when he gets to be a man and receives \$20 a week, he should do \$30 worth of work; a man receiving \$30 should do \$40 worth of work, and so on until, say, the salary reaches \$75, and then the laborer can give himself somewhat of a rest, that is to say, about \$50 worth of work will satisfy his employer. Labor brings its market value, and is seldom overpaid, oftener underpaid. It is the experience—the "Know How"—that brings the money.—*Philadelphia Ledger.*

THE center of bulb culture in Holland, says *Gartenflora*, is still at Haarlem, as it has been during two centuries and a half. Hyacinths are especially in favor just now, and ground suitable for their cultivation has sold for as much as \$13,500 an acre, as against about \$1,000 given for land of other kinds. The expense of cultivation is placed at about \$300 an acre for hyacinths and \$160 for tulips; and it is noted that artificial manures are never used. Narcissus is also grown in vast quantities near Haarlem, chiefly for exportation to England. Formerly the export trade in cut flowers was enormous, one Haarlem firm having exported in a single season 10,000 cases; but an agreement was last year entered into by a majority of the Dutch florists to abandon the sale of cut flowers as competing with the interests of purchasers of bulbs. Attempts have been made to extract the perfume of hyacinths, but only with moderate success, especially from the commercial point of view.



**Standard Water Pipes.**

At the meeting of the American Water Works Association, recently held at Louisville, Mr. S. B. Russell read a short paper on standard water pipes. At present the consumer orders pipes of the desired diameter and thickness. The manufacturer chooses the pattern nearest to this diameter, and calculates a core to give the required weight, but rarely gets the exact internal diameter. This results in considerable annoyance and some loss to the consumer. In America there are 14 sizes of 6 inch pipe, between 27 lb. and 33 lb. weight per foot; and still they scarcely keep within limits of  $2\frac{1}{2}$  to 5 per cent variation in the weight. Wrought iron and lead pipes do not vary so much. Mr. Russell thought the Association were eminently fitted to improve the present condition of affairs, and any plan approved by them would, he said, probably come into general use. The standard series should fix the number of classes, five or six weights for each size. The weights per foot must also be fixed; and the uniformity of pattern (one of which might suffice for each size) would then greatly simplify the joint question. In St. Louis there are four classes of 30 inch, and two classes of other size of pipe, and only one pattern for each diameter.

**The Antiquity of Bronze.**

According to an analysis made by Professor Berthelot, the scepter of Pepi I., an Egyptian king of the Sixth Dynasty, consists of almost pure copper. The scepter in question belongs to the British Museum, and, as a special favor to Minister Waddington, the Museum authorities consented to give a portion of the precious object to be submitted to Professor Berthelot for analysis. Some filings from the inside—the scepter is hollow—weighing less than  $\frac{1}{2}$  grain, or exactly 0.0248 gramme, were detached for examination. The Professor has found them to consist of a reddish metal, slightly oxidized, and a quantitative analysis, correct within one-tenth of a milligramme, has proved the substance to be pure copper, without any admixture of tin, and doubtful traces of lead. His conclusions are that, since archæologists agree in placing Pepi's reign at about 4,000 years before the Christian era, the introduction of bronze, both in the Old World and in America, occurred very nearly at the same period, and at an epoch not much farther back than fifty or sixty centuries from the present time.

**UNIVERSAL HAND LATHE.**

The accompanying cut shows a new hand lathe which has just been placed on the market by the Brown & Sharpe Manufacturing Company, of Providence, R. I.

As shown in the cut, it rests upon a table; but it is frequently used as a bench lathe, and is furnished without the table. To prevent the bed from being sprung or twisted when the lathe is set, there is a pin in the top of one of the legs, which allows it to swivel sufficiently to compensate for any slight unevenness of the floor or bench. The other leg is firmly secured to the bed.

The top of the bed is flat, and is scraped to surface plate. It affords a bearing over its entire width for the foot stock and slide or other rests. The bearing surfaces of these are also scraped.

The foot stock is fastened to the bed by a clamp screw, and can be easily shifted or taken from the bed. Its spindle moves in a steel bushing, and is operated by a hand lever which has its fulcrum on an adjustable stud back of the spindle. This spindle may be clamped in any position, and has a movable stop, which serves to limit the forward motion when brought against the adjustable stop screw.

The spindle and boxes of the head stock are steel, hardened and fitted by grinding. The hole through the spindle is one-half inch in diameter the greater part of its length, and tapers at the front to three-fourths of an inch in diameter. The spindle bearings are thoroughly protected from grit and dust and are lubricated from beneath.

The tool holder guides on the head and foot stock may be set in or out, and enable the lathe to be used for turning small shafts, studs, screws, etc., either straight or taper.


The overhead works consist of two counter-shafts. The first has tight and loose pulleys, 6 inches in diameter,  $2\frac{1}{2}$  inches face, also a three-step cone pulley. The second has a corresponding cone pulley and a driving pulley. The hangers have adjustable and self-oiling boxes.

The lathe swings 9 inches over bed and receives 14 inches between centers. The weight of the lathe complete, ready for shipment, is about 500 pounds. The usual accessories are furnished.

The Brown & Sharpe Manufacturing Company has just issued a very fully illustrated pamphlet on the construction and use of the hand lathe, which they will be pleased to forward on application.

**NEW MICRO-SURFACE GAUGE.**

The annexed illustrations represent a new tool for obtaining fine measurements on the planer or surface plate. In general appearance it is not unlike the ordinary gauge used for that purpose. It, however, possesses many advantages over all others in being provided with graduated staff and micrometer screw, reading to thousandths of an inch. In the hands of skilled


**MICROMETER SURFACE GAUGE.**

workmen this tool is capable of the finest adjustment. The staff is milled out to receive a steel rod, passing through its entire length, and is graduated for a distance of five inches. The slide, carrying the pointer, is connected to the central rod by means of a clamping screw, that allows it to be moved instantly and held firmly in any position.

The rod is threaded at the top for a distance of one inch to correspond with the internal thread of the cap. The latter revolves on the staff, and each revolution moves the slide or pointer carrier twenty-five one-thousandths of an inch up or down.

The pointer is held between clamping collars, and revolves with them to any position around their axis, and it may be moved from end to end through the collars. A milled thumb nut secures the pointer in any position in which it may be placed.

The measurement is obtained by first setting the pointer roughly, as in all ordinary surface gauges, the fine adjustment being effected by turning the cap. A movable collar on the slide is then brought up to the proper graduation for beginning, and a similar collar

**UNIVERSAL HAND LATHE.**

on the staff is made to coincide with the cap, 0 to 0. This first measurement may be taken from the surface the tool rests on, or from any test block or scale, and carried anywhere from that to the extreme height of pointer at its greatest elevation, which is about 12 inches with the one furnished. Longer pointers may

be substituted, thus making the capacity of the gauge practically without limit.

This tool is the invention of Mr. Edgar Smith. It is made by Chandler & Farquhar, 177 Washington Street, Boston, Mass., who may be addressed for further information.

**Telephone Vibrations Made Visible.**

At a recent meeting of the Physical Society, Berlin, Dr. Frohlich made a further communication in connection with his older, resultless experiments on the objective demonstration of the vibrations of a telephone disk, in order to describe his new method by which positive results had been obtained. In his earlier experiments he employed manometric flames, and endeavored to photograph their movements with the help of a rotating mirror; now, however, he attaches a small mirror to the iron plate of the telephone, and from this the light of an electric lamp is reflected on to a polygonal rotating mirror, from which it falls upon a screen. The vibrations of the plate were thus made visible on the screen, and since each side of the polygonal mirror cast its own image, when the mirror was rotated the curves were seen moving over the screen. The more rapidly the mirror was rotated the slower did the curves move over the screen, and when the rotation was as rapid as the vibration of the plate, the curves became stationary and could thus be exactly observed and drawn. These luminous curves could also be photographed. The speaker had employed this method in a series of researches on certain electrical phenomena which might influence the efficiency of the telephone. Thus the action of alternating currents, of self-induction, of the rise and fall of the current on making and breaking, of the introduction of electromagnets, and of other conditions, were studied by means of the altered mode of vibration of the telephone plate. The speaker had further obtained a graphic record of the vibrations of the telephone plate when vowels and consonants are sung and spoken into it. Many other problems may, by the above method, be brought nearer to their solution.

**The International Congress of Medical Jurisprudence.**

The above congress commenced their session for the year 1889 on June 4, at Steinway Hall, in this city. It closed on June 7. The officers elected included Dr. Clark Bell as president, with Prof. John J. Reese, of Pennsylvania, ex-Judge Noah Davis, of New York, and a number of eminent physicians and others as vice-presidents and secretaries. A paper by Prof. R. Ogden Doremus on the "Marsh Test for Arsenic" brought out an interesting discussion. A man was charged with poisoning his wife, but immediately after her death the undertaker had as a preservative injected the body with an arsenical solution. It was agreed that in such a case no distinction could be drawn between the fatal arsenic and that of the embalming solution. Other subjects discussed during the meeting touched upon the degree of responsibility for crime. "Alcoholism, Inebriety, and Suicide," and the subject of "Insanity and Responsibility," including the topic of the innocent insane, and the necessity for their treatment in separate institutions or divisions from the criminal insane, were the subjects of papers and discussions. Toward the close of the session the subject of electricity as the mode of inflicting the death penalty was spoken of. The city institutions for the insane were inspected, and after some social features, including a dinner, the session adjourned.

**Painting Floors.**

A French writer observes that painting floors with any color containing white lead is injurious, as it renders the wood soft and less capable of wear. Other paints without white lead, such as ocher, raw umber, or sienna, are not injurious, and can be used with advantage. Varnish made of drying lead salts is also said to be destructive, and it is recommended that the borate of manganese should be used to dispose the varnish to dry. A recipe for a good floor varnish is given as follows: Take two pounds of pure white borate of manganese, finely powdered, and add it little by little to a saucepan containing ten pounds of linseed oil, which is to be well stirred and raised to a temperature of 360° Fahr. Heat 100 pounds of linseed oil in a boiler till ebullition takes place, then add to it the first liquid, increase the heat and allow it to boil for twenty minutes. Then remove from the fire and filter the solution through cotton cloth. The varnish is then ready for use, two coats of which may be used, with a final coat of shellac, if a fine polish is required.

**The New Explosive.**

A correspondent calls our attention to an error of spelling. Grisoutite is correct. The spelling grisonite was a typographical error.

## RECENTLY PATENTED INVENTIONS.

## Engineering.

**BOILER FEEDER.**—Albert F. Jones, Salem, Mass. This invention covers a novel combination and arrangement of parts in a simple form of boiler feeder, designed to be effective and automatic in operation, while at all times keeping the water level in the boiler at the desired height.

**GAS WASHER.**—Joseph De Brouwer, Bruges, Belgium. This invention relates to apparatus for purifying gas used for heating and illuminating purposes, providing a single machine, essentially after the pattern of a turbine, whereby the gas may be exhausted from the retorts, cleared of all its impurities, condensed and properly carbureted and prepared for consumption, the invention covering various novel features of construction and arrangement of parts.

**SMOKE CONSUMER.**—James C. Butler, Quincy, Ill. This invention covers a construction whereby steam taken by a pipe from the dome of the boiler is carried immediately below the grate, and superheated and introduced into the furnace just in advance of the bridge wall, causing a combustion designed to be so perfect that there can be no accumulation of soot, and the gases will all be consumed.

## Railway Appliances.

**RAIL FASTENER.**—Charles Netter, New York City. Bolts project upward through the tie at each side of the rail flange, each bolt having a transverse slot for the reception of a key which bears on the rail flange at one end, the other end of the key being secured to the tie by a locking bolt or an ordinary screw bolt.

**CAR STARTER.**—Gustav Schmidt, Rheine, Prussia, Germany. This is a form of pinch bar, with a lever handle and a plate extension of the base to place under the rim of the car wheel, there being mounted in an opening in the base a grooved roller having flanges with ratchet teeth, the roller being adapted to fit over the crown of the rail, while a pawl prevents the roller from revolving backward when the load is heavy or the rails wet.

**CABLE GRIP.**—Charles S. Chapman, Kansas City, Mo. The grip heads are connected to a fixed frame, a movable frame being arranged for connection with the toggles of the grip, and a link pivoted in the movable frame, while a crank is pivoted in the fixed frame and pivotally connected to the lower end of the link, a lever being mounted upon the pivots of the crank, the parts being readily adjustable as they become worn.

**STATION INDICATOR.**—Victor L. Cunningham, No. 3 East Swan St., Buffalo N. Y. A casing is provided containing cards bearing the names of stations, the cards being arranged to be moved forward by an endless belt, with an escapement for allowing them to be dropped out of sight, and devices for operating the belt and escapement, so that a series of indicators may be placed on the different cars of a train and operated simultaneously by the conductor or engineer.

## Mechanical.

**SAW SWAGING MACHINE.**—Thomas B. Hite, Seattle, Washington Ter. The construction of this machine is such that the entire device may be fastened to a wall or bracket, while the saw to be operated on is suspended in proper position by a rope or other means, the invention covering various novel parts and combinations in a machine designed to be simple and durable in construction and very effective in operation.

**CLEANER FOR COTTON GIN SAWS.**—John C. Godwin, Lloyd, Texas. This cleaner is placed directly below the saws, secured on a shaft mounted to rotate in the usual manner, and consists principally of a drum provided with radially arranged pairs of arms, forming forks, and adapted to press against the faces of the saws, to clean them while running, the arms being made of spring material, such as horn, whalebone, etc., about four pairs of arms being usually employed for one saw.

**WATER WHEEL.**—Lee Middleton, Clarksville, Mo. This water wheel is supported upon a vertical shaft between the top and bottom beams of a sliding frame moving in uprights in the mill race, the wheel being of novel construction, and being designed to be raised out of water when the operator desires to stop the rotary motion of the shaft.

## Miscellaneous.

**GAS BURNER AND HEATER.**—Daniel S. Robilliard and Charles G. Davies, of Quebec, Canada. This is a burner designed for heating and cooking purposes, wherein an effective admission and expansion of gas and air is designed to be attained to give the best results from the least quantity of gas, the burner being held in suspension by a yoke within the stove opening or other desired place.

**WINDOW.**—Gustav J. Dolliner, Hamburg, Germany. Each of the casements, by this invention, is made with two separate points of rotation, the double hinges of the casements being so made that they descend when opened inward, the windows being adapted to be opened both inward and outward, while a tight connection will always be made between the window frame and the closed window casements.

**FRAME FOR FANNING OUT PAPER.**—James C. Oliver, Bergen Point, N. J. This invention covers a device to obviate the necessity of skilled labor in pushing out the edges of sheets, envelope blanks, or cards, designed to overlap sufficiently to leave a series of border spaces, and consists of a baseboard with longitudinal side strips and notched strips adjustable thereon, with other novel features.

**RAZOR STROP.**—George H. Coursen, Baltimore, Md. This strop consists of a rotatable

wheel, made of wood sections glued or cemented together, each end of the wheel being somewhat in the shape of a truncated cone, the wheel having a circumferential jacket, one end of the jacketed wheel being covered with emery or other sharpening composition, while the other end is left plain.

**TRUNK FIXTURE.**—James B. Porter, Yarmouth, Nova Scotia, Canada. This is a lid or cover stay consisting of a spring plate with keeper, a segmental bar being secured to the lid and sliding between the keeper and the spring plate, whereby the lid, when carried upward to an open position, will be automatically locked to place.

**WASHING TEXTILE FABRICS.**—James S. Farmer, Salford, Lancaster County, England. This invention covers an apparatus consisting of rotating spider wheels, near the peripheries of the arms of which are mounted slotted or perforated hollow cylinders on the ends of links pivoted loosely to the disks or arms, for the better washing, cleansing, and treating of textile fabrics.

**REFINISHING RUBBER BLANKETS.**—Ferdinand H. Kogge, West Hoboken, N. J. This invention covers a method designed especially for use with rubber blankets of lithographic presses, by applying to the worn surface a composition consisting of varnish, gutta percha, white lead in oil, in specified proportions, allowing the material so applied to dry, and finally smoothing and polishing the surface.

**BRAKE FOR DUMB WAITERS.**—Hugh Donohoe, New York City. A brake wheel is secured on the shaft supporting the carriage pulley, and a second wheel held in line with the brake wheel, there being a pin with a wedge held between the two pulleys, a brake shoe engaging the brake wheel and supporting the pin, while a lever operates on the brake shoe, and weighted ropes are connected with the lever to counterbalance and operate it, affording a simple device for rapidly braking the main pulley.

**SYRINGE.**—Martin Overlach, Frankfurt-on-the-Main, Germany. This is a glass syringe so constructed that it may be readily taken apart for cleaning, while the joints at the ends of the cylinders will be tight, the invention permitting the use of glass tubes having absolutely flat walls and no threads, while all the parts are exposed to view.

**VETERINARY INSTRUMENT.**—Benjamin Champlin, Cortland, Ill. This invention consists of a lance having a rounded head, with shoulders projecting beyond the sides of the lance, the instrument being for use mainly to effect a permanent remedy for hard milking in cows.

**HORSE DETACHER.**—John J. Peter, Campbellsville, Ky. This invention covers a novel construction and combination of parts whereby, at the will of the driver, the traces secured at their rear ends to the vehicle may be detached at their forward ends from the hames, and the backing strap may also, as the horse moves forward, be detached from the breeching.

**EGG TRAY FOR INCUBATORS.**—John W. Hile, Valley Falls, Kansas. The drawer has inclined surfaces on which the eggs are supported, in connection with a division board having egg-shaped openings into which the eggs are fitted and held in an inclined position, the division board sliding in the drawer to turn the eggs, whereby a larger percentage of eggs will hatch out chicks, in a stronger and healthier condition.

**WICK RAISING ATTACHMENT.**—Patrick J. Glynn, Highland, N. Y. This invention relates to lamps having a wick-raising gear mechanism, and provides an improved device so arranged that the burner may be readily taken off and put on, and the wick-raising gear mechanism properly adjusted, so that it may always be effectively operated.

**COMBINATION LOCK.**—Irvin A. Shaw, Kinsley, Kan. The sliding bolt has a longitudinal slot communicating with a circular opening, in connection with a shaft having a flat part received by the slot of a circular tumbler, whereby when the flat part and tumbler slot are perpendicular to the bolt slot the bolt will be locked, and when turned flatwise the bolt may be retracted, the tumbler sliding with the bolt, the operator being guided by the sound of a spring engaging a turning ratchet wheel.

**CHECKREIN HOOK.**—George W. Moliere, Ocean View, Cal. This invention consists of a checkrein hook with two parallel shanks, secured to the harness saddle by a screw passing through both shanks, there being no projection on the under side of the shank, so that when the saddle padding becomes compacted or worn, the back of the horse is not chafed.

**REIN HOLDER.**—William F. Turman, Weatherford, Texas. This is a device which may be attached to a vehicle by bolts or straps, as most convenient, in which to place the reins when a horse is left standing, or it may be utilized to hold an animal's head back when unruly, the reins being drawn back when possible, while the animal cannot draw them forward.

**GRAB LINK FOR TRACE CHAINS.**—Joseph E. Giroux, Alpena, Mich. This is a fastening for securing the chain in the gripping portion of the link so that there will be no danger of the chain slipping within the grab link, and when once adjusted it may be held securely, while in unhitching it is only necessary to detach the chain from the trace tug and let the chain hang on the whiffletree.

**WATER HEATER.**—Simon Spiro, Birmingham, Ala. This invention covers a novel form of fire pot to be placed in a vessel or receptacle containing the water to be heated, so that the heat given out will do its work most efficiently, while the fire pot will be held against displacement, and is convenient to carry by bails or handles.

**GATE.**—William C. Hooker, Abingdon, Ill. This invention covers an improvement on a former patented invention of the same inventor, providing a gate of simple and durable construction, which is locked automatically, and can be easily opened and closed from either side of the roadway.

**TROUSERS STRETCHER.**—David F. McNair, Wilkesbarre, Pa. This device consists essentially of two frames pivoted together, with clamp bars sliding therein, and wedge bars hinged to the frames, and a lock bolt, for retaining rigidly the top and bottom of a pair of trousers, and also adapted to be conveniently manipulated to stretch them and remove the bagging from the knees.

**PERCOLATOR.**—Thomas Boyce, New York City. The vessel for containing the menstruum and drug has a chamber in its bottom under the strainers, a suction tube leading down into the chamber and having a closure at its upper end, a discharge cock leading from the chamber, and a tube depending from the cock and having an upward bend at its lower end, the device being also adapted for use as a filter.

**SELF-CLOSING HATCHWAY.**—Frank J. Gridley, New York City. This invention relates to improved safety devices for elevator shafts, etc., whereby, should a fire happen in the building, the devices retaining the shaft doors will be released by the heat and the doors be permitted to automatically close, cutting off the draught up the shaft.

**PHOTOGRAPHIC PLATES.**—Walter S. Cullen, Kearney, N. J. This invention consists in an adjustable rack for washing and drying photographic negatives and positive plates, whereby the plates are securely held, and the rack is readily adjustable to different sized plates, while it may be folded for transportation and used by photographers in moving from place to place.

**MAP EXHIBITOR.**—William A. Taylor, Washington, D. C. This exhibitor is made in cabinet form to constitute a neat article of furniture, the sides of the casing having guides, outside of which weights are arranged, connected by cords with the maps, the edges of which are bound with sheet brass, to keep them from wear, the whole allowing of the ready exhibition of any one of a series of maps.

SCIENTIFIC AMERICAN  
BUILDING EDITION.

JUNE NUMBER.—(No. 44.)

## TABLE OF CONTENTS.

1. Elegant plate in colors, showing elevation in perspective and floor plans of a field stone residence, costing about nine thousand five hundred dollars. Page of details, etc.
2. Plate in colors of a cottage costing three thousand two hundred dollars. Perspective elevation, floor plans and details.
3. Engraving of the new Federal building to be erected at Worcester, Mass. Cost two hundred and fifty thousand dollars.
4. A cottage of moderate cost lately erected at Bedford Park, New York. Perspective and floor plans.
5. Plans and perspective of a convenient stable erected at Bedford Park, N. Y.
6. A handsome residence lately erected at Chattanooga, Tenn., from designs by Blotterwick & Penn, architects. Cost ten thousand dollars complete. Plans and perspective elevation.
7. A residence at Florence, Northampton, Mass. Cost ten thousand dollars complete. Perspective and floor plans.
8. Engraving of a half-timbered house at Chester, England.
9. View and plans of a fine barn lately erected near Providence, R. I.
10. A modern residence at Belle Haven Park, Greenwich, Conn. Perspective and floor plans.
11. A handsome house in the colonial style lately erected at "Renolds Terrace," Orange, N. J., at a cost of fifteen thousand dollars complete. Chas. A. Gifford, of London, architect. Perspective elevation and floor plans.
12. A cottage at Bedford Park, New York. Cost eight thousand five hundred dollars. Plans and perspective.
13. Engravings of the great Eiffel tower at the French exhibition.
14. St. Cloud Prebyterian Church, Orange, N. J. Potter & Robertson, architects, New York. Perspective elevation and floor plan. Cost seven thousand five hundred dollars.
15. Miscellaneous Contents: Brick piers.—Home decorations.—Delights of color.—Foundations in alluvial deposits.—Portland cement and sea water.—The effect of moisture on wood.—The weeping larch, illustrated.—Nashville's estimating rules.—Selected lumber.—The science of dry rot.—Sewage a protection against the teredo.—Ornamental borders, with illustrations.—Hot air vs. steam.—The new Catholic cathedral at Pekin.—Advantage of sanitary measures.—Which are the hardwoods?—An ideal living room.—A water motor for elevators, illustrated.—Granite rust.—Ventilating grates, illustrated.—French building laws.—Mahogany.—Artistic wood work, with illustrations.—Stains for mortar and plaster.—An enduring tin roof.—Wood filling and finishing.—Shell fish marbles.—Fire-resisting ceilings.

The Scientific American Architects and Builders Edition is issued monthly. \$2.50 a year. Single copies, 25 cents. Forty large quarto pages, equal to about two hundred ordinary book pages; forming, practically, a large and splendid MAGAZINE OF ARCHITECTURE, richly adorned with elegant plates in colors and with fine engravings, illustrating the most interesting examples of Modern Architectural Construction and allied subjects.

The Fullness, Richness, Cheapness, and Convenience of this work have won for it the LARGEST CIRCULATION of any Architectural publication in the world. Sold by all newsdealers.

MUNN & CO., PUBLISHERS,  
361 Broadway, New York.

## Business and Personal.

The charge for insertion under this head is One Dollar a line for each insertion; about eight words to a line. Advertisements must be received at publication office as early as Thursday morning to appear in next issue.

Special facilities for manufacturing light machinery, hardware, and novelties. Stamping, presswork, punches, dies, and special tools. Correspondence invited. Rockaway Manuf. Co., Rockaway, N. J.

Small model dynamo castings, \$2.75, \$3.75, and \$4.75. Circular. H. Wellman Mfg. Co., box 49, Catlettsburg, Ky. Rubber Belting, all sizes, 77½ per cent from regular list. All kinds of Rubber Goods at low prices. John W. Buckley, 156 South Street, New York.

Capitalists wanted to form stock company to introduce patent air ship. See Sci. Am., June 8, 1889. Address H. A. J. Kieckert, 134 Rivington St., New York.

For Sale—Patent floor cleaner. Simple, durable, and adapted to all floors. H. V. Shaw, Lawrenceburgh, Ind.

For the best Hoisting Engine for all kinds of work, address J. S. Mundy, Newark, N. J.

Guild & Garrison, Brooklyn, N. Y., manufacture steam pumps, vacuum pumps, vacuum apparatus, air pumps, acid blowers, filter press pumps, etc.

Engineers wanted to send their addresses and receive free a 25 cent book, "Hints and Suggestions for Steam Users." Lord & Co., 11 S. 9th St., Philadelphia, Pa.

Steel name stamps (1-16, 3-32, or ½ in. letters), 15c. per letter. F. A. Sackmann, 16 Huron St., Cleveland, O.

For the latest improved diamond prospecting drills, address the M. C. Bullock Mfg. Co., Chicago, Ill.

## Ball Engine.

Automatic cut-off. Ball Engine Co., Erie, Pa.

Presses & Dies. Ferracnte Mach. Co., Bridgeton, N. J.

The Holly Manufacturing Co., of Lockport, N. Y., will send their pamphlet, describing water works machinery, and containing reports of tests, on application.

Screw machines, milling machines, and drill presses. E. E. Garvin & Co., Laight and Canal Streets, New York.

Pedestal tenoner. All kinds woodworking machinery. C. B. Rogers & Co., Norwich, Conn.

Perforated brass for well points, lamps, etc. The Robert Aitchison Perforated Metal Co., Chicago, Ill.

Billings' Patent Breech-loading Single Barrel Shotgun. Billings & Spencer Co., Hartford, Conn.

Steam Hammers, Improved Hydraulic Jacks, and Tube Expanders. R. Dudgeon, 24 Columbia St., New York.

Safety Elevators, steam and belt power; quick and smooth. The D. Frisbie Co., 112 Liberty St., New York.

"How to Keep Boilers Clean." Send your address for free 96 p. book. Jas. C. Hotchkiss, 120 Liberty St., N. Y.

The best Coffee roasters, coolers, stoners, separators, polishers, scourers, glossing apparatus, milling and peaberry machines; also rice and macaroni machinery, are built by The Hungerford Co., Broad and Front Sts., N. Y.

Lathes for cutting irregular forms. Handle and spoke lathes. I. E. Merritt Co., Lockport, N. Y.

Band saws, with tipping table. All kinds woodworking machinery. Rollstone Machine Co., Fitchburg, Mass.

Split Pulleys at low prices, and of same strength and appearance as Whole Pulleys. Yocom & Son's Shafting Works, Drinker St., Philadelphia, Pa.

Send for new and complete catalogue of Scientific and other Books for sale by Munn & Co., 361 Broadway, New York. Free on application.

## Notes &amp; Queries

## HINTS TO CORRESPONDENTS.

Names and Address must accompany all letters, or no attention will be paid thereto. This is for our information, and not for publication.

References to former articles or answers should give date of paper and page or number of question.

Inquiries not answered in reasonable time should be repeated; correspondents will bear in mind that some answers require not a little research, and, though we endeavor to reply to all, either by letter or in this department, each must take his turn.

Special Written Information on matters of personal rather than general interest cannot be expected without remuneration.

Scientific American Supplements referred to may be had at the office. Price 10 cents each.

Books referred to promptly supplied on receipt of price.

Minerals sent for examination should be distinctly marked or labeled.

(944) N. G. B. asks: Is the No. 16 magnet wire used on the armature and field magnet double-covered and paraffined or the single-covered costing about 40 cents per pound? Does it make any difference if the layers of the field magnet do not lie close against each other, and the ends of the separate pieces abut? A. Single cotton-covered wire without paraffine is the kind used in the construction of the small motor. Double-covered would be preferable if there were room for it on the armature. The double-covered and paraffined you refer to is probably office wire, which will not answer. Irregular winding will make no serious difference in the power of the field magnet. The strips of which the field magnet is composed should lie as near together as possible, the ends being arranged to abut.

(945) C. W. S. asks: In increasing the size or linear dimensions one-half of the simple electric motor described in SUPPLEMENT 641, with what size magnet wire should I wind the armature and magnet coils to get the most power with bichromate battery? Would it answer to use a copper rim of proper dimensions for a commutator instead of screws? A. Wind the field magnet and the armature with wire of the size given in the article referred to, and place as many coils as possible on the armature. A copper rim divided into segments will answer.

(946) H. V. B. asks in reference to the phonograph described in SUPPLEMENT, No. 133: 1. Can the wax cylinder used at the present time be substituted for the tinfoil? A. It could if the recording point was of proper shape; as described it would probably answer, but a blunt point should be used for the



reproduction of the message. 2. Can you give me any information as to the component parts of the wax used on these cylinders? A. No; it is not disclosed. 3. If not, kindly give directions for making a composition which will answer the same purpose. A. Try beeswax or paraffine wax mixed with spermaceti. 4. At what speed should the shaft which carries the cylinder revolve? A. About two revolutions per second. 5. Can the foil be replaced on the cylinder after being taken off when it has received the impressions of the needle? A. No. 6. How long should a cylinder last with careful handling? A. A wax cylinder can reproduce its message several hundred times.

(947) S. C. P. writes: 1. How long will the Eagle brand of condensed milk keep when the can is opened and but little taken out at a time? A. No period can be assigned; all depends on the atmospheric conditions, etc. Keep in the can upon the ice in a closed refrigerator. 2. Is there any danger of its being "chemicalized" when so opened? A. No; it will only turn sour and decompose. 3. Would it be better to empty the contents into a porcelain receptacle? A. No; do not attempt to transfer it. 4. How can I renew antique oak furniture that has been scratched by foreign substances and blistered by heat? A. Rub down to a surface with fine sand paper, smooth with ground pumice stone and water, varnish, and rub down with pumice stone and water. Repeat the varnishing and rubbing down process two or three times, finally varnish and polish with rotten stone and oil, and rub with olive oil and water on palm of hand. Use cloth scraps for the pumice and a piece of chamois for the rotten stone. 5. May coal oil be used on such furniture and a piano as a polish without injury to the articles? A. Use olive oil and water on the palm of the hand. Do not use coal oil.

(948) O. F. S. asks: How does a diamond compare with an electric light carbon as a conductor of electricity? A. The diamond is a very poor conductor of electricity, far inferior to the other forms of carbon. 2. What is the punishment for marking an article "patent" when the article has not been patented. A. The penalty by section 4901 of the patent laws is fixed at not less than one hundred dollars, with costs, half the penalty to go to the person who shall sue for the same, and the other to the use of the United States. It is to be recovered by suit in a United States district court.

(949) T. & Co. ask: Can you inform us if it would be practical to take pieces of tortoise shell and weld them together, by soaking the pieces of shell in hot water, then pressing them together? A. Provide a pair of tongs or pincers or tongs, file the point off to a feather edge, wet the surfaces and apply the pincers hot, following them with water. The tongs or pincers must not be too hot. Try them on paper, as you would curling irons for hair. The joint must be absolutely free from grease. This receipt is given by good authority.

(950) D. E. S. asks: 1. What is beeswax mixed with to make the wax to take a mould to electroplate? What parts of each? A. Melt 9 pounds beeswax and mix it with 1 pound Venice turpentine, and after mixture stir in 5 ounces of the best and finest flint and mix thoroughly. 2. Will a battery made from zinc, copper, blue vitriol, and rain water answer for a battery to electroplate with? If not, what would be a good one? A. Yes; two or three such cells would answer. The Smee battery is excellent. For batteries we refer you to our SUPPLEMENT, Nos. 157, 158, 159. 3. Will the book on Electrotyping, by J. W. Urquhart, C.E., in your catalogue, be of any help to a beginner? Does it give the formula and treatment in plain terms of the process of electrotyping? A. The work is an excellent one, and is clear and simple in its treatment of the subject. Consult also our SUPPLEMENT, No. 310, for electroplating processes.

(951) H. W. B. asks: 1. Can you give me a formula for liquid to keep fruits, preserving their natural color, also for insects and fish, preserving their natural color? A. For natural objects in general use, alcohol. For insects no liquid, is needed, as they can be kept in the open air. 2. Best method of killing insects? A. Mix cyanide of potassium with plaster of Paris and water to consistency of cream and allow it to set in the bottom of a bottle, filling about one inch in depth. Keep corked. Put the insect when caught into the bottle, and it will soon die. 3. Manual for mounting objects for microscope and collecting of diatoms. A. We refer you to "Practical Microscopy," by Davis, \$3, also Clarke's "Objects for the Microscope," \$1.25. 4. What is your professional opinion on palmistry? Is there anything in it? A. There is absolutely, nothing in it.

(952) C. M. W. asks: 1. Can the blow-pipe furnace described in SCIENTIFIC AMERICAN, May 4, be made to burn gasoline instead of gas, as we have no gas here, and if so, how should it be used? A. The air blast should be blown through a tin or iron box containing gasoline. It will probably pick up enough in going over its surface to give a good flame. It can be made to work better by hanging cloths from top to bottom within the box. 2. How can I melt coin silver? A. In a crucible in a blacksmith's forge, using dried carbonate of soda, borax or common salt as a flux. 3. One steam horse power is equal to how many man power? A. Eight man power is equal to one horse power.

(953) G. T. G. asks: Is there any difference between one mile square and one square mile? A. One mile square denotes a rectangular area measuring one mile on each side. One square mile denotes the area of such a piece irrespective of its shape. Thus a piece of land one-half mile wide and two miles long would be one square mile in area, but would not be one mile square. The first expression denotes shape and size, the second size alone.

(954) G. T. writes: Do you know of any preparation that may be used for writing upon glass so that the writing will be etched upon the surface? I cannot coat the articles with varnish or wax and apply fluorine acid in the usual manner, and writing with the acid alone gives a blurred result. A. Equal parts of hy-

drofluoric acid, fluoride of ammonium, and dry precipitated sulphate of baryta are rubbed together in a porcelain mortar. They are then transferred to a lead, platinum, or gutta percha dish, and fuming hydrofluoric acid is added while the mixture is rapidly stirred with a gutta percha rod until it is of creamy consistency and the impression made by the rod quickly disappears. The sulphate of baryta is best made by precipitating chloride of barium solution with sulphuric acid, filtering, washing, and drying the precipitate at 248° Fah. Much depends on the quality of the sulphate of baryta. On no account let the hydrofluoric acid touch the skin, as it has the most serious effects. The compound is sold as "diamond ink," and should be purchasable in this city.

(955) T. W. asks: Will it take less hydrogen to run a gas engine than common gas? Will it take less hydrogen to run a steam engine than common gas. In both cases, in what proportion? A. It will take four or five times as much hydrogen measured by volume to produce the same quantity of mechanical energy as is produced by common gas, whether by the steam or gas engine.

(956) C. C. S. asks for a formula for making an ink eraser. A. Ink is erased by oxalic acid compounds, such as solution of the acid, pure or mixed with citric acid in equal parts. A stick of binoxalate of potash is sometimes used, which is rubbed over the spot previously moistened. Javelle water or other bleaching agents may be used. As a mechanical eraser India rubber with which ground pumice stone has been mixed before vulcanization can be used.

(957) W. C. H.—The sample sent is a clay rock containing pyrites, of no value as far as discernible.

(958) J. P. T. writes: 1. I have recently had a lightning conductor put on my house, composed of 49 strands of copper wire, and I am told it is not necessary to insulate where it is fastened to building. Is this so? A. Insulation is unnecessary. 2. Can you recommend a good treatise on sugar manufacturing plant, by means of diffusion, and also the roller system? A. We recommend Lock's "Sugar, or Hand Book for Planters and Refiners," price \$10. This work treats the subject thoroughly and is an excellent work.

(959) Reader asks for a good hard negative varnish.

A. Shellac.....	1 1/4 oz.
Mastic.....	1/4 "
Oil of turpentine.....	1/4 "
Sandarac.....	1 1/4 "
Venice turpentine.....	1/4 "
Camphor.....	10 grs.
Alcohol.....	20 fl. oz.

The varnish is applied by pouring on from the bottle, at one end of the plate, and then oscillating the plate from side to side and tilting it at the end until the whole surface is covered.

(960) H. W. R. asks how concentrated lye or potash is made, such as I find put up in tin boxes on the market. We burn in our furnace hickory dust, and the ashes are strong. This, for want of a market, we throw away. I would like to know if I could convert so small a quantity (100 horse power boiler) into potash at a profit and if the method be complicated or expensive. I know in the old times they made lye by putting the ashes in a hopper arranged over a barrel, pouring water on the ashes, which drained the lye into the barrel. A. A solution of lye is made substantially as you describe. By boiling down to dryness, crude carbonate of potash is obtained, called potash. This should find a market with soap makers, dealers in or manufacturers of chemicals, etc. The concentrated lye sold we believe to be caustic soda.

(961) W. R. writes: I have made a stick of carbon as directed in SCIENTIFIC AMERICAN, vol. ix., No. 20. It proves satisfactory, and I have used it in place of the platina of a Grove battery, but it does not seem to supply the same current as the platina, being only a small piece, about 4 inches long, 1 inch wide, and 1/4 inch thick. The platina is 3 inches long by 1 inch wide. I would therefore be very much pleased if you would tell me through Notes and Queries how thick I should make the carbon to supply the same current as the platina in the battery mentioned. I should prefer it to be round carbon. A. You should have recarbonized your rod several times. There is scarcely room in a Grove porous cell for a large carbon. Better use a regular Bunsen cell, if you wish to use the carbon electrode. The carbon should not be less than 1 inch in diameter.

(962) A. V. B. asks (1) whether there are any known means of making the atmosphere visible. A. No. 2. If there is any way of producing an absolutely constant direct electric current, by mechanical means. A. All such currents in practice have pulsations or variations. At the sacrifice of efficiency for weight, a constant current can be obtained.

(963) C. K. asks whether a magnet will attract iron or steel in a vacuum. A. A vacuum has absolutely no effect upon magnetic attraction.

(964) J. A. W. asks what preparations are used to make combustible matter non-combustible. A. Tungstate of soda, borax, and other salts are largely used for this purpose. Various formulas are given in the books. The Techno-Chemical Receipt Book contains several.

(965) J. S. W. asks for a quick drying mucilage that will not mould, or sour in a warm room or weather. A. Dissolve 2 pounds gum arabic in 2 1/2 quarts of water, add enough oil of cloves to perfume it slightly. This will be about ten or twenty drops.

(966) J. E. P. writes: In Cristiani's Perfumery it specifies liquid carmine for coloring extract of rose (page 240) and extract of raspberry (page 241). Can you give me a formula for liquid carmine which is to be used in coloring the above extracts? A. Soak powdered cochineal in alcohol and water, 3 parts cochineal, 40 to 50 parts alcohol, and 200 parts water. Add

just enough carbonate of soda to the solution to color it. A very small quantity will suffice.

(967) H. G. asks whether there are any surface indications by which it is possible to ascertain the existence of gas, oil, or salt below the surface of land, or if not, whether the fact can be ascertained in any other way than actually sinking or boring a test well. A. Boring or sinking a well is the only certain way. The geological identification of strata may lead to a probability of the presence of one or the other, but there is no certainty in the matter.

#### TO INVENTORS.

An experience of forty years, and the preparation of more than one hundred thousand applications for patents at home and abroad, enable us to understand the laws and practice on both continents, and to possess unequal facilities for procuring patents everywhere. A synopsis of the patent laws of the United States and all foreign countries may be had on application, and persons contemplating the securing of patents, either at home or abroad, are invited to write to this office for prices, which are low, in accordance with the times and our extensive facilities for conducting the business. Address MUNN & CO., office SCIENTIFIC AMERICAN, 361 Broadway, New York.

### INDEX OF INVENTIONS

For which Letters Patent of the United States were Granted

June 4 1889,

#### AND EACH BEARING THAT DATE.

[See note at end of list about copies of these patents.]

Addressing machine, J. W. H. Reisinger.....	404,732
Aerated water, manufacturing and bottling, O. Avedyk.....	404,462
Air, apparatus for purifying atmospheric, W. Hibbert.....	404,621
Alarm. See Burglar alarm.	
Animal catching device, T. Wickham.....	404,583
Armature core for dynamos, J. F. Kester.....	404,713
Axle boxes, dust guard for car, L. Goulloud.....	404,701
Axle, carriage, F. Lebel.....	404,635
Baking and roasting pan, C. Preston.....	404,558
Bar. See Grate bar.	
Barns, composite truss for, J. W. Evans.....	404,612
Battery. See Galvanic battery.	
Bed bottom and means for tightening and supporting the same, J. E. Moore.....	404,722
Beds, appliance for sick, G. S. Brown.....	404,681
Bevel, G. H. Waggoner.....	404,451
Bicycle, J. F. Breux.....	404,771
Bicycle, S. D. Reynolds.....	404,562
Binder, temporary, W. F. Wakeman.....	404,513
Blackboards, crayon rack for, A. J. Douglass.....	404,389
Blast furnaces, dust catcher for, F. H. Treat.....	404,807
Board. See Center board. Wash board.	
Boiler cleaning apparatus, J. T. Obenchain.....	404,425
Boiler feed, J. H. Rae.....	404,730
Boiler feed regulator, W. O. Gunkel.....	404,400
Boiler feeder, A. F. Jones.....	404,629
Boiler furnace, E. Barrett.....	404,378
Bolt heading machines, slot making attachment for, S. Uren.....	404,580
Bolting reel, J. Warrington.....	404,810
Boots and shoes, lasting, D. F. Willis.....	404,455
Bottle case, folding, E. L. Walker.....	404,809
Bottle stopper, G. Rehuss & Co.....	404,797
Bottle stopper, J. J. Sands.....	404,799
Box. See Fire alarm signal box. Stuffing box.	
Box fastener, L. Peterson.....	404,728
Bracket. See Lamp bracket.	
Brake. See Car brake.	
Brush, C. J. Bailey.....	404,588
Buckle, R. G. & R. L. Henry.....	404,406
Buckle, bale tie, E. L. Clark.....	404,383
Buggy top spring, C. V. Pugh.....	404,434
Burglar alarm, Roads & Griffith.....	404,734
Burner. See Gas burner. Hydrocarbon burner. Lamp burner. Oil burner.	
Bustle, H. E. Rheubottom.....	404,798
Cable grip, C. S. Chapman.....	404,601
Calcing furnace, D. Lewis & Co.....	404,720
Camera. See Photographic camera.	
Camera stand, W. H. Fuller.....	404,396
Car body, J. T. Goodfellow.....	404,585
Car brake, Abbott & Killin.....	404,373
Car brakes, device for operating, R. A. Kiskadden.....	404,418
Car coupling, J. E. Bull.....	404,468
Car coupling, King & Reed.....	404,717
Car coupling, S. S. McKean.....	404,725
Car coupling, V. Nusly.....	404,552
Car coupling, I. Stout.....	404,743
Car coupling, A. Swenson.....	404,575
Car door, C. L. Ward.....	404,755
Car dumping apparatus, A. F. Thayer.....	404,447
Car for mines, tool, J. Treweek.....	404,510
Car heating apparatus, C. A. Marrder.....	404,492
Car roof, G. A. Roberts.....	404,735
Car starter, G. Schmidt.....	404,563
Cars, apparatus for shifting, R. Ramsay.....	404,656
Cars, coupler for air brake mechanism on railway, A. J. Wisner.....	404,760
Cars, mechanism for extinguishing the lights in railway, I. N. Tillson.....	404,749
Cars, motive mechanism for railway, H. F. & G. F. Shaw.....	404,441
Card clothing thereto, device for holding cylinders while attaching, I. E. Comins.....	404,685
Card grinding roller, J. S. Dronsfeld.....	404,606
Card or ticket case, A. Allen.....	404,515
Card, playing, R. F. Foster.....	404,732
Carding engines, machine for securing clothing to, E. Ashworth.....	404,587
Carding or other machines, cylinder for, G. O. Wickers.....	404,812
Carriage, M. Haughey.....	404,405
Carriage top, J. T. Noonan.....	404,650
Carrier. See Hay carrier. Straw carrier.	
Cart, T. Hardy.....	404,402
Cart, road, M. Barnes.....	404,672
Cartridge belt, A. J. Blix.....	404,677
Cartridge crimping tool, F. Wichelhaus.....	404,811
Case. See Bottle case. Card or ticket case.	
Casting core for, G. H. Bennett.....	404,673
Casting core ingots, E. L. Clark.....	404,383
Centerboard, steering, J. H. Hunt.....	404,626
Chain fastener, H. B. Kelley.....	404,631

Chain link machines, feed mechanism for, J. D. Storie.....	404,742
Chains, grab link for trace, J. E. Giroux.....	404,615
Chair. See Convertible chair. Folding chair. Portable chair.	
Checkrein hook, G. W. Mofere.....	404,643
Chisel, carpenter's, T. H. Palmer.....	404,554
Churn, W. M. Shira.....	404,569
Churn, H. Sommerfeld.....	404,443
Cigar holder, H. Machfanz.....	404,644
Cleaner. See Slat cleaner.	
Cleansing and polishing compound, J. H. Despain.....	404,387
Closet. See Water closet.	
Cloth into strips, machine for cutting, J. G. McCarter.....	404,645
Cloth marking implement, N. Harris.....	404,452
Cloth sponging machine, W. Heddon.....	404,620
Clothes wringer, Parker & Vokes.....	404,653
Clutch and brake, friction, T. W. Capen.....	404,776
Coffee cleaning machine, C. J. Pickett.....	404,430
Coffee pot, F. A. Hovey.....	404,707
Coffer dam, H. P. Kirkham.....	404,718
Coffin, E. C. Manning.....	404,639
Collar fastener, J. Himmelstein.....	404,409
Collars, mould for making glass pads for horse, D. Barker.....	404,766
Combination lock, I. A. Shaw.....	404,568
Combing machines, dabbing brush apparatus for, J. L. Ballantyne.....	404,376
Convertible chair, A. Botkin.....	404,767
Coupler, steam tight, T. M. Jenks.....	404,710
Coupling. See Car coupling. Hose coupling. Pipe coupling.	
Cultivator, J. W. Johnson.....	404,711
Cultivator, C. H. Ruddell.....	404,437
Curtain ring, J. Lines.....	404,637
Curtains, refinishing, C. Imandt.....	404,543
Cutlery, R. Daine.....	404,385
Cutter. See Fireman's electric wire cutter. Straw cutter.	
Cutting apparatus, Lindstrom & Jernberg.....	404,548
Door check, A. Hursh.....	404,627
Door fastener and alarm, combined, S. Goulden.....	404,617
Door lock and hinge, combined, Binsfeldt & Chateau.....	404,590
Door lock, sliding, S. W. Hunton.....	404,412
Double pointed pin, J. H. Birch.....	404,675
Drawer, furniture, J. H. Knaus.....	404,740
Drawer pull, E. P. Nobbs.....	404,495
Dray, J. L. Davis.....	404,658
Drift and drill catch, J. T. Kenworthy.....	404,646
Drill. See Ratchet drill.	
Driving and belt shifting mechanism, E. R. Hyde.....	404,709
Duplicating apparatus, G. H. Davis.....	404,778
Dynamos, brush spring for, J. F. Kester.....	404,715
Dynamos, detachable brush holder for, J. F. Kester.....	404,712
Electric cable, terminal, R. H. Widdicombe.....	404,813
Electric currents, distribution by alternating, O. B. Shallenberger.....	404,566
Electric currents, system of generators for alternating, O. B. Shallenberger.....	404,567
Electric machine, dynamo, W. Hochhausen.....	404,484
Electric machine or motor regulator, J. F. Kester.....	404,714
Electric machine regulator, dynamo, E. P. Clark.....	404,802
Electric meter for alternate currents, M. M. M. Slattery.....	404,801
Electric motor, C. S. Bradley.....	404,465
Electric motor, H. B. Slater.....	404,681
Electric motor, alternating current, C. S. Bradley.....	404,466
Electric motor and regulator, A. Gartner.....	404,533
Electric motor regulator, A. Gartner.....	404,783
Electric motors, safety attachment for, W. S. Paca.....	404,651
Elevator. See Hydraulic elevator.	
Elevator, A. B. Wall.....	404,808
Elevator and conveyor, C. J. Seymour.....	404,660
Engine. See Hydraulic engine. Rotary steam engine. Steam engine.	
Exercising machine, J. J. Sleeper.....	404,802
Exhaust mechanism, J. D. Smith.....	404,739
Feed water heater, J. H. Vail.....	404,512
Feed water heater and regulator, N. Clute.....	404,683
Felt boot, J. Vail.....	404,512
Fence post, J. Kelly.....	404,788
Fibrous materials, disintegrating, R. P. Pictet.....	494,431
File, document or letter, E. W. Woodruff.....	401,438
Filing receptacle, A. L. Brown.....	401,712
Filtering apparatus, J. W. Hyatt.....	404,708
Fire alarm signal box, non-interfering, J. J. Rud-dick.....	404,438
Firearm, breech-loading, C. G. Bonehill.....	404,380
Firearm, breech-loading, Dicer & Barker.....	404,779
Firearm sight, J. W. Carver.....	404,598
Fire escape, G. W. Worden.....	404,514
Fireman's electric wire cutter, Woodhouse & Forster.....	404,687
Fish hook guard, C. W. Teed.....	404,747
Flood gate, H. A. Wright.....	404,761
Fly trap, J. E. Packard.....	404,727
Fly trap, A. S. Schuyler.....	404,565
Folding chair for steamers, etc., C. F. Batt.....	404,589
Fork guard, R. B. B. Clayton.....	404,777
Freight elevating and transporting apparatus, W. H. Russell.....	404,658
Fruit stoning machine, Briggs & Leach.....	404,517
Fuel saving device, A. C. Greenlee.....	404,702
Furnace. See Boiler furnace. Calcining furnace. Warm air furnace.	
Furnace grate, self-feeding, L. Hopercraft.....	404,706
Galvanic battery, W. Frishmuth.....	404,699
Gas, apparatus for manufacturing, W. Clark.....	404,520
Gas, apparatus for the manufacture of, J. F. Toraya.....	404,750
Gas, apparatus for the manufacture of fuel and illuminating, Harrison & Egner.....	404,404
Gas burner, device for automatically operating the stop cock of a, C. M. Rider.....	404,733
Gas generator, compound hydrocarbon, R. Ferguson.....	404,527
Gas washer, J. De Brouwer.....	404,606
Gate. See Flood gate. Railway gate.	
Gate, W. C. Hooker.....	404,625
Gate, J. Walker.....	404,754
Generator. See Gas generator. Steam generator.	
Governor, steam valve, F. B. Pettengill.....	404,796
Grain binder, O. O. Storie.....	404,506
Grain binding machine, F. Harper.....	404,479
Grain cleaning machine, J. F. Wilson.....	404,456
Grain, heating and steaming, W. H. Smith.....	404,571
Grain press, W. Preston.....	404,655
Grate attachment, J. J. Mitchell.....	404,423
Grate bar, G. M. Knight.....	404,719
Grate for ranges, stoves, or furnaces, S. J. Buz-zini.....	404,595
Grinding machine, R. Conrader.....	404,686
Grinding machine, C. H. Henderson.....	404,787
Grinding mill runner, J. C. Dell.....	404,607
Grindstone and mechanism for the same, H. A. Axtell.....	404,670
Guard. See Fish hook guard. Fork guard. Rail-way guard.	

Hair curling device, C. A. G. Piane	404,501
Hair curling implement, B. L. Toquet	404,664
Hammer, A. L. De Vol	404,388
Hammock and canopy support, combined, J. Gifford	404,614
Harrow, pulverizing, C. La Dow	404,791
Hat forming machine, G. Yule	404,459
Hat holder and packing frame, W. M. Levy	404,636
Hat wire machine, B. McCusker	404,647
Hatchway, self-closing, F. J. Gridley	404,618
Hatchway, self-closing, E. J. Herman	404,705
Hay cap, W. R. Thatcher	404,577
Hay carrier, J. Farrell	404,525
Heater. See Feed water heater. Water heater.	
Heating device, steam, H. A. Kroeschell	404,419
Hinge, spring, J. R. Payson, Jr.	404,556
Holder. See Cigar holder. Hat holder. Necktie holder. Rein holder. Sash holder. Ticket and stamp holder. Vessel holder.	
Hook. See Checkrein hook.	
Hose coupling, Pearce & Merrill	404,429
Hotel room register, C. H. Greenleaf	404,398
Huller. See Seed huller.	
Hydraulic cylinder for controlling steam cylinders, C. F. Elmes	404,523
Hydraulic elevator, self-regulating, W. E. Nickerson	404,726
Hydraulic engine, C. E. Foster	404,528
Hydrocarbon burner, A. L. Shore	404,442
Hydrocarbon burner, W. Snee	404,804
Incubator, W. Knopf	404,634
Indicator. See Station indicator.	
Induction coil, J. F. Kelly	404,630
Ingot mould, E. L. Clark	404,381
Inkstands, etc., self-closing cover for, I. W. Heylinger	404,589
Iron direct from its ores, reducing, C. J. Eames	404,589
Iron or steel, determining the temper of, C. A. Casperson	404,600
Jack. See Lifting jack.	
Joint. See Rail joint. Railway rail joint.	
Key seats, machine for cutting, T. W. Broomell	404,679
Ladders, adjustable attachment and extension for fire, J. W. Tully	404,511
Lamp and toilet case, combined, F. Maehr	404,421
Lamp bracket, piano, W. A. Smith	404,570
Lamp burner, Argand, P. J. Foulon	404,474
Lamp shade, H. Hohenstein	404,540
Lamps, filament for incandescent electric, T. D. Bottom	404,463
Lantern, portable electric, W. Frishmuth	404,698
Lantern, tubular, R. Hermance	404,538
Latch, gate, P. Dyer	404,391
Lens, applanatic, H. L. H. Schroder	404,506
Lifting jack, Shaffer & Bairstow	404,800
Light. See Submarine search light.	
Liquors, apparatus for purifying and aging, S. G. Cabell	404,682
Lock. See Combination lock. Door lock. Nut lock.	
Lock, A. S. Boice	404,516
Locomotive cab seat, G. W. Stone, Jr.	404,662
Loom picker, E. S. Grinnell	404,478
Loom shuttle binder, S. J. Noiseux	404,649
Loom shuttle box mechanism, J. Mathieson	404,640
Loom stop mechanism, E. Herzig	404,407
Mandrel, expandable, P. H. Griffin	404,477
Map exhibitor, W. A. Taylor	404,805
Mash machine, R. Garich	404,532
Measuring vessel, T. S. Cockcroft	404,603
Medicine, cough sirup, Maxwell & Meddaugh	404,422
Metal, apparatus for mixing molten pig, W. R. Jones	404,415
Metal, mixing molten pig, W. R. Jones	404,414
Metallic wheel, F. H. Ensign	404,611
Meter. See Electric meter. Rotary meter.	
Mould. See Ingot mould. Vault light mould.	
Motor. See Electric motor. Spring motor. Water current motor.	
Motor for operating swinging devices, C. J. B. Gaume	404,613
Mower, H. Lindstrom	404,549
Mower attachment, lawn, F. A. Deland	404,690
Napkin holder table attachment, J. M. Hinds	404,410
Necktie fastener, J. Reid	404,436
Necktie holder, G. A. Huewe	404,411
Nut lock, G. P. Fuller	404,530
Oculists and opticians, trial frame for, A. L. Smith	404,808
Oil burner, G. S. Paine	404,428
Oil from oil wells, device for ejecting, W. Geiser	404,397
Oiling wheels, device for, F. W. Harris	404,481
Ornamental vessel or article, T. B. Gibson	404,785
Oven, baker's, J. H. Meier	404,441
Overflow trap, water seal, E. J. Whitlock	404,759
Packing for metallic boxes, H. R. Gillingham	404,700
Packing for piston rods, J. P. Murray	404,493
Pan. See Baking and roasting pan.	
Paper, dampening apparatus for rolls of, W. Scott	404,505
Paper, machine for making perforations in, S. Wheeler	404,582
Paper, making perforations in, S. Wheeler	404,581
Paper package, toilet, O. H. Hicks	404,622
Paperette, A. Buhler	404,594
Paring squashes, machine for, F. L. Webster	404,452
Pens or pencils, spring holder or clasp for, F. J. W. Fischer	404,697
Percolator, T. Boyce	404,591
Petroleum or similar substances, apparatus for burning, Guignard & Schweizer	404,399
Photographer's retouching machine, Girvin & Loff	404,534
Photographic camera shutter, R. E. M. Bain	404,375
Photographic plates, rack for washing and drying, W. S. Cullen	404,605
Piano action, S. Hansing	404,704
Pin. See Double pointed pin.	
Pipe coupling, C. F. Murrel	404,413
Pipe coupling, steam, F. Hanson	404,786
Pipe wrench, E. S. Boynton	404,770
Pipe wrench, C. L. Dunham	404,751
Pipe wrench, J. T. Hawkins	404,619
Planing and surfacing machines, feed roller for, L. P. Hoyt	404,486
Planing machine, wood, F. J. Plummer	404,493
Plow, ditching, R. H. Nogar	404,424
Plow, sulky, J. A. Garber	404,476
Plow, swivel, Gale & Tremblay	404,531
Plow, wheel, G. Kimball	404,716
Pocket books or other articles, frame for, L. Messer	404,721
Pocket or note book, E. Weissbrod	404,758
Polishing compound, G. W. Hastings	404,483
Portable chair, L. Engebretsen	404,610
Post. See Fence post.	
Postal cards, machine for packaging, W. H. Bunce	404,773
Pot. See Coffee pot.	
Pot and protector for seedlings, etc., combined, W. L. Wright	404,586
Press. See Grain press.	
Pressure regulator, fluid, W. Ross	404,508, 404,504

Protector. See Tree protector.	
Pulp, etc., from fibrous plants, machine for scraping the, R. G. Ward	404,756
Pump, stock, G. W. Schroeder	404,737
Pumping rig, well, C. C. Stover	404,744
Punching machine, hydraulic, C. C. Klinik et al.	404,633
Quicksand, apparatus for raising, H. Stoltze, Sr.	404,741
Radiator loops, machine for assembling, H. H. Taylor	404,746
Rail joint, D. R. Atkinson	404,764
Railway, electric, W. Cannell	404,489
Railway, electric, L. Daft	404,687
Railway gate, A. J. McDonald	404,724
Railway grip, cable, J. H. Pendleton et al.	404,499
Railway grip, cable, C. C. Tiers et al.	404,576
Railway guard, automatic, J. V. Reams	404,435
Railway rail fastener, C. Netter	404,550
Railway rail joint, E. P. Jervey	404,487
Railway signal, A. J. Wisner	404,457
Railway signals and points, working and interlocking, Hill & O'Donnell	404,408
Railway track, J. Haish	404,401
Railways, drip pan for elevated, E. A. Trapp	404,751
Railways, endless belt for grips for cable, J. H. Pendleton et al.	404,500
Railways, guide pulley for cable, Pendleton & Moss	404,498
Railways, means for operating trains upon cable, Pendleton & Bryson, Jr.	404,497
Railways, track moistening apparatus for electric, E. D. Priest	404,559
Range, G. H. Phillips	404,502
Ratchet drill, H. Brinkmann	404,592
Razor, F. Ascheuer	404,763
Reciprocating machinery, mechanism for cushioning traversing beds of, H. P. Feister	404,394
Reel. See Bolting reel.	
Register. See Hotel room register.	
Regulator. See Boiler feed regulator. Electric machine regulator. Electric motor or motor regulator. Electric motor regulator. Pressure regulator.	
Rein holder, W. F. Turman	404,579
Ring. See Curtain ring.	
Ring dies, making, K. Ecaubert	404,562
Rods, machine for manufacturing cylindrical, H. H. Post	404,654
Roller. See Card grinding roller.	
Roller for leveling snow and roads, I. B. Babcock	404,671
Rotary meter, P. Ball	404,374
Rotary steam engine, H. L. Phelps	404,557
Rubber boot, E. F. Bickford	404,674
Rubber boot or shoe, J. L. Joyce	404,416
Ruler, Brown & Payette	404,593
Saddle, harness, Aschenbach & Theobald	404,689
Sash fastener, R. J. Buchanan	404,467
Sash holder, Hammarlund & Larson	404,537
Sash lift, W. A. Williamson	404,666
Saw, hand power, J. M. Vaughn	404,753
Saw swaging machine, T. B. Hite	404,623
Saws, apparatus for straightening, D. Simonds	404,738
Saws, cleaner for cotton gin, J. C. Godwin	404,616
Scraper, road, G. N. Miller	404,793
Scraper, road, O. E. Moats	404,794
Scraping machine, road, M. G. Bunnell	404,774
Screen. See Window screen.	
Seat. See Locomotive cab seat.	
Seed huller, cotton, Fee & Zerbe	404,696
Separator. See Slime separator.	
Sewing machine cover, N. R. Van Horn	404,752
Sewing machine, shoe, J. Treharn	404,448
Sewing machines, cutting mechanism for button-hole, Ostrom & Boynton	404,427
Sewing machines, shuttle and race mechanism for, F. D. Parker	404,555
Shackle, James & Goodenough	404,544
Sheet metal package, F. G. Caldwell	404,536
Shirt, B. Galland	404,475
Signal. See Railway signal.	
Skate roller, C. J. Kintner	404,547
Slate cleaner, J. M. McFarland	404,795
Sled, L. P. Pickett	404,432
Slime separator, P. H. Dunagan	404,521
Smoke consumer, J. C. Butler	404,775
Smoker's set, W. S. Whiting	404,685
Spinning spindle support, J. Duffy	404,609
Spring. See Buggy top spring. Vehicle spring.	
Spring motor, R. Faries	404,526
Stamp canceler, B. Summers	404,574
Stamping or other machines, safety apparatus for, T. J. Holmes	404,624
Stand. See Camera stand.	
Station indicator, V. L. Cunningham	404,384
Steam engine, A. H. F. Straub	404,573
Steam generator, J. A. Eno	404,524
Steam generator, W. Snee	404,740
Steel direct from ore, producing, W. F. M. McCarty	404,723
Steering apparatus, A. C. Dunn	404,472
Stereotyping, matrix for, Schreiner & Schott	404,564
Stilt, H. Temple	404,896
Stools or chairs, spring back for, W. P. James	404,628
Stopper. See Bottle stopper.	
Stove and utensils, portable cooking, A. S. Tomkins	404,578
Stove or range attachment, C. B. Tefft	404,748
Stovepipe anchor and flue cleaner, L. H. Oldfield	404,553
Stoves, automatic extinguisher for car, Levy & Dagwell	404,420
Stoves, safety oil can attachment for vapor, H. Ruppel	404,459
Straw carrier, G. Akerson	404,460
Straw cutter, W. C. Rayless	404,879
Street surfaces, guide bar for lining up the curves of, J. M. Mack	404,491
Stuffing box, L. C. S. Frick	404,529
Submarine search light, A. L. Dutton	404,390
Switch points, mechanism for operating, J. M. Swem	404,446
Switch stands, lock house for, W. J. McCarthy	404,646
Swivel, H. E. Kelley	404,632
Swivel, Sears & Kelley	404,659
Syringe, vaginal, Zerze & Yount	404,762
Table, J. M. Davis	404,689
Tannic extract, purifying, L. Saabach	404,440
Teeth, filling, E. C. Taylor	404,745
Teeth, mould for the manufacture of artificial, W. R. Hall	404,703
Telegraph apparatus, E. B. Shafer	404,507
Telegraph, duplex fire, S. A. Chase	404,519
Telegraph, fire alarm, S. A. Chase	404,518
Telephone support, C. W. Brown	404,680
Telephone transmitter, E. S. Drake	404,471
Terret with separable shank, E. E. Hardy	404,403
Ticket and stamp holder, A. Williamson	404,584
Ticket selling machine, automatic, J. W. Vaughn	404,450
Tire, wheel, R. W. Donmoyer	404,692
Tongs, roofing, Blum & Listeman	404,673
Tools to handles, device for securing, Thompson & Torrey	404,668
Trap. See Fly trap. Overflow trap.	
Tree protector, H. L. Webber	404,757
Trimmer. See Wick trimmer.	

Trousers stretcher, D. F. McNair	404,648
Truck, car, G. E. Blaine	404,678
Tubs, etc., cover for butter, H. C. Carter	404,597
Umbrella exhibitor, Harrington & Carter	404,490
Umbrella or parasol, F. S. Evans	404,636
Unken device, G. F. Oehmen	404,426
Under vest, C. F. North	404,551
Valve, Egner & Harrison	404,392
Valve for air brakes, release, G. A. Boyden	404,768
Valve gear, M. I. Welch	404,453
Valve gear for compound engines, J. C. H. Stut	404,509
Valve, pressure regulating or reducing, E. Andre	404,596
Valve, safety, J. M. Colven	404,684
Valve, time, P. G. Hubert	404,542
Vault light mould, D. Barker	404,765
Vehicle, H. Arenberg	404,461
Vehicle, folding, J. McBoyle	404,494
Vehicle spring, S. H. Raymond	404,500
Vehicle, two-wheeled, W. Page	404,496
Velocipede, A. Easthope	404,693
Velocipede, H. A. King	404,490
Vessel holder, J. P. Eustis	404,694
Veterinary mouth speculum, C. E. Palmer	404,652
Voltmeter, L. Daft	404,470
Wagon body raiser, W. S. Bourne	404,464
Warm air furnace, B. F. Reynolds	404,561
Wash basin, P. G. Hubert	404,541
Wash board, L. N. Poe	404,729
Washer. See Gas washer.	
Washing machine, R. Joel	404,545
Washing machine, Z. Randel	404,731
Water closet, A. Elmendorf	404,393
Water conveyer, F. D. Dowd	404,780
Water current motor, K. G. Johnson	404,488
Water heater, E. N. Gates	404,784
Water heater, S. Spiro	404,572
Water meters, sealing device for, G. S. Follansbee	404,395
Water purifying apparatus, O. S. Howes	404,485
Water reservoir, H. Daue	404,386
Water wheel, L. Middleton	404,642
Weather strip, A. M. Stodard	404,445
Wheel. See Metallic wheel. Water wheel.	
Wheel, M. C. Root	404,657
Whipbarrow, W. E. Kilborn	404,789
Whip socket, E. Allen	404,698
Wick trimmer, J. L. Sanford	404,736
Windmill, A. J. Corcoran	404,604
Window, H. Maurer	404,792
Window screen, J. S. White	404,454
Wire matting, I. Kinney	404,417
Wire stretcher, E. Guthridge	404,536
Wire weaving apparatus, H. Steddom, Jr.	404,444
Wood, convertible machine for grooving and sawing, E. F. Barnes	404,377
Woodworking tool, Joslin & Lawrence	404,489
Wrench. See Pipe wrench.	
Wrench, E. S. Boynton	404,769
Wringer. See Clothes wringer.	

## DESIGNS.

Bottle, W. Baker, Jr.	19,125
Box, H. F. Whitman	19,143
Canister, R. Staudinger	19,141
Cigar box, W. P. Wilcox	19,144
Dressing case, T. J. Collins	19,130
Fireplace lining, E. L. Caley	19,127
Inhaler tube, J. F. Chesebro	19,128
Latch case, R. W. E. Christesen	19,129
Lattice or mesh work, F. A. Winslow	19,145
Oil cloth, C. T. & V. M. Meyer	19,132 to 19,138
Roofing plate, metallic, L. L. Sagendorph	19,139
Seggar, T. A. Bell	19,126
Textile fabric, L. Haslam	19,131
Tey cap exploder, O. A. Wheeler	19,142
Toy money safe, H. Schedler	19,140

## TRADE MARKS.

Belts or bands, electric, J. E. Hetherington	16,680
Bicycles, tricycles, and kindred vehicles, and their parts and attachments, Starley Brothers	16,702
Biscuits, crackers, wafers, and similar articles, J. D. Gilmore & Co.	16,688
Bitters, C. Pickard	16,674
Butter, L. H. Ballow & Co.	16,682
Cements or compositions for roofing and paving, J. B. Hinchman	16,692
Cigars, Buckingham, Swope & Co.	16,684
Cigars, M. Lopez & Co.	16,666 to 16,669
Cigars, F. Suarez & Son	16,676
Cigars, smoking tobacco, and cigarettes, Pine Needle Cigar Company	16,673
Coffee scourers and polishers, Hercules Manufacturing Company	16,691
Cough mixture, F. M. Jaques	16,693
Face wash, J. P. McGill	16,672
Feather pillows, F. E. Little	16,694 to 16,696
Flour, wheat, D. A. Luckenbach	16,670
Game board, S. T. F. Sterick	16,675
Ginger, carbonated, White Rock Mineral Springs Company	16,678
Gloves, kid, J. Roeckl	16,699
Glue, J. Herold	16,689
Insect powders and like preparations, W. H. Sayre	16,700
Knitting cotton, J. T. Morehead & Co.	16,697
Mask fasteners, C. H. Dessart	16,685
Mattresses and springs for the same, spring, B. Fitch & Co.	16,686
Mineral waters, ginger ale, lemonade, tonic drinks, and similar liquids, Arcadian Mineral Spring Company	16,680
Newspaper, H. Gerard	16,687
Newspaper, J. A. Hart	16,682
Optical goods of all kinds, A. J. Lloyd	16,665
Optical instruments, C. F. Prentice	16,698
Paper for ledgers, L. L. Brown Paper Company	16,683
Perfumed articles, such as soap, sachet powders, and the like, Ladd & Coffin	16,664
Photographs, appliances for taking, C. Spiro	16,701
Pills, R. MacFarland	16,671
Remedy for piles, C. E. Ashmead	16,681
Tea, P. H. Kelly Mercantile Company	16,663
Tobacco for smoking and chewing, plug and cut, Thompson, Moore & Co.	16,677
Watch movements, American Waltham Watch Company	16,679
Whisky, M. & K. Gottstein	16,661

A printed copy of the specification and drawing of any patent in the foregoing list will be furnished from this office for 25 cents. In ordering please state the name and number of the patent desired, and remit to Munn & Co., 361 Broadway, New York.


Canadian Patents may now be obtained by the inventors for any of the inventions named in the foregoing list, provided they are simple, at a cost of \$40 each. If complicated the cost will be a little more. For full instructions address Munn & Co., 361 Broadway, New York. Other foreign patents may also be obtained.

## Advertisements.

Inside Page, each insertion - - - 75 cents a line.  
Back Page, each insertion - - - \$1.00 a line.

The above are charges per agate line—about eight words per line. This notice shows the width of the line, and is set in agate type. Engravings may head advertisements at the same rate per agate line, by measurement, as the letter press. Advertisements must be received at publication office as early as Thursday morning to appear in next issue.

## USE ADAMANT WALL PLASTER



It is Hard, Dense, and Adhesive. Does not check or crack. It is impervious to wind, water, and disease germs. It dries in a few hours. It can be applied in any kind of weather. It is in general use. Licenses granted for the mixing, using, and selling. Address  
**ADAMANT MFG. CO.**  
71 E. Genesee Street,  
Syracuse, N. Y.

**ICE-HOUSE AND COLD ROOM.—BY R. G. Hatfield.** With directions for construction. Four engravings. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, 59. Price 10 cents. To be had at this office and of all newsdealers.

## Patent Foot Power Machinery Complete Outfits.

Wood or Metal workers without steam power, can successfully compete with the large shops, by using our New **LABOR SAVING Machinery**, latest and most improved for practical shop use, also for Industrial Schools, Home Training, etc. Catalogue free.  
**Seneca Falls Mfg. Co.**  
635 Water Street, Seneca Falls, N. Y.

**ICE-HOUSE AND REFRIGERATOR.** Directions and Dimensions for construction, with one illustration of cold house for preserving fruit from season to season. The air is kept at a constant



## A New Book on Assaying.

The Newest and Best in the English Language.  
It Leads all others!!

JUST READY.

## THE ASSAYER'S MANUAL

An Abridged Treatise on the Doctrines of Examination of Ores and Furnace and other Artificial Products. By Bruno Keri, Professor of the Royal School of Mines; Member of the Royal Technical Commission for the Industries, and of the Imperial Patent Office, Berlin. Translated from the German by William T. Brann, Editor of "The Techno-Chemical Receipt Book," etc. Second American Edition, edited with extensive additions by F. Lynwood Garrison, Member of the American Institute of Mining Engineers, Iron Institute, Verein Deutscher Eisenhüttenleute, etc. Illustrated by 87 engravings. 351 pages 8vo. Cloth, price.....\$3.00

By mail, free of postage, to any address in the world. ABSTRACT OF CONTENTS.—GENERAL DIVISION.—I. Mechanical Manipulations. II. Chemical Operations. III. Assay Furnaces. IV. Assay Vessels. V. Balances and Weights. VI. Tools and Implements. VII. Assay Reagents. SPECIAL DIVISION.—I. Lead. II. Copper. III. Silver. IV. Gold. V. Platinum. VI. Nickel. VII. Cobalt. VIII. Zinc. IX. Cadmium. X. Tin. XI. Bismuth. XII. Mercury. XIII. Antimony. XIV. Arsenic. XV. Uranium. XVI. Tungsten. XVII. Chromium. XVIII. Manganese. XIX. Sulphur. XX. Fuels. Appendix. Index.

A circular of 8 pages quarto, giving the full Table of Contents of this Important Book, as well as a new List of Leading Books on Metal Mining, Metallurgy, Mineralogy, Assaying, Chemical Analysis, etc., sent free to any one in any part of the world who will send his address.

The above or any of our Books sent by mail, free of postage, at the publication price, to any address in the world.

Our New and Revised Catalogue of Practical and Scientific Books, 84 pages, 8vo, and our other Catalogues, the whole covering every branch of Science applied to the Arts, sent free and free of postage to any one in any part of the world who will furnish his address.

HENRY CAREY BAIRD & CO.,  
INDUSTRIAL PUBLISHERS, BOOKSELLERS & IMPORTERS  
810 Walnut St., Philadelphia, Pa., U. S. A.

## ARCHITECTURAL BOOKS.

Useful, Beautiful, and Cheap.

To any person about to erect a dwelling house or stable, either in the country or city, or any builder wishing to examine the latest and best plans for a church, school house, club house, or any other public building of high or low cost, should procure a complete set of the ARCHITECTS' AND BUILDERS' EDITION OF THE SCIENTIFIC AMERICAN.

The information these volumes contain renders the work almost indispensable to the architect and builder, and to persons about to build for themselves they will find the work suggestive and most useful. They contain colored plates of the elevation, plan, and detail drawings of almost every class of building, with specifications and approximate cost.


Four bound volumes are now ready and may be obtained, by mail, direct from the publishers or from any newsdealer. Price, \$2.00 a volume. Stitched in paper covers. Subscription price, per annum, \$2.50. Address and remit to

MUNN & CO., Publishers,  
361 Broadway, New York.


## NEW YORK BELTING AND PACKING CO.

JOHN H. CHEEVER, Treas.

15 PARK ROW, New York.



OLDEST AND LARGEST Manufacturers in the United States of  
VULCANIZED RUBBER FABRICS  
For Mechanical Purposes.  
RUBBER BELTING,  
Packing, Hose,




Vulcanite Emery Wheels, Rubber Mats, Matting &amp; Treads

SALESROOMS:—Philadelphia, 308 Chestnut St.; Boston, 52 Summer St.; Chicago, 151 Lake St.; Minneapolis, 28 South 2d St.; Cincinnati, 161-165 W. Pearl St.; Cleveland, 176 Superior St.; San Francisco, 14 & 16 Main St.; Detroit, 16-24 Woodward Avenue. European Branch, Pickhuben 5 Hamburg (Freihafengebiet), Germany.



## The National Galvanic Battery

Unequaled for Door Bells, Telephones, Gas Lighting, Burglar Alarms, etc. Specially adapted for medicinal use. Platinum Carbon Connection. Perforated Body. The only real improvement of a Porous Cup. No soaking required. Works instantly. Will last a lifetime. Simple, Clean, Durable. Write for circulars and prices. The National Galvanic Battery Co., 247 Main Street, Cincinnati, O. 18 Cortlandt Street, New York.



## THE MOTOR OF 19th Century.

The Best on manufactured gas and the only one that makes its Own Gas. Can be used Any Place, to do Any Work, and by any One. For circulars, etc., address

Charter Gas Engine Co.,  
P. O. Box 148, Sterling, Ill.  
Branch House, 152 Lake St., Chicago.



Economy, Reliability, Simplicity, Safety. W. J. Dougherty, 470 Canal Street, New York Agency.

ADVICE TO YOUNG MECHANICAL ENGINEERS.—Address by Prof. Perry, to his students at the Finsbury Technical College. A paper of great value and interest to all working engineers. One engraving. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 661. Price 10 cents. To be had at this office and from all newsdealers.

## THE RICHARDS OIL ENGINE




The Safest, Most Economical, and Most Convenient Engine. No Boiler, No Steam, No Coal, No Ashes, No Danger, No Extra Insurance, No Engineer, and next to no Attendance. Started instantly with a match. Speed and fuel completely regulated by the governor. All expense ceases when the engine stops. BINGHAMTON HYDRAULIC POWER CO., Binghamton, N. Y., U. S. A.

VOLNEY W. MASON & CO.,  
FRICTION PULLEYS CLUTCHES and ELEVATORS  
PROVIDENCE, R. I.



MOSS ENGINEERING CO. 335 PEARL ST. NEW YORK  
OUR SPECIALTY: FIRE ILLUSTRATED CATALOGUES  
BY OUR NEW LITHO PROCESS.  
Send Green Stamp for Most Recent Catalogue.



## EVEN THE BROWNIES MAKE PHOTOGRAPHS


WE MAKE ALL KINDS OF PHOTOGRAPHIC OUTFITS FOR AMATEURS.

Send for our New Illustrated Catalogue and copy of Modern Photography.

ROCHESTER OPTICAL CO.,  
18 AQUEDUCT ST., ROCHESTER, N. Y.

## DO YOUR OWN PLATING

Either in Gold, Silver, or Nickel, and Electrotyping. Complete sets of each, with practical instruction that any person may learn the art easily. Send for catalogue and price list to THOS. HALL, Mfg. Electrician and Optician, 19 Bromfield Street, Boston, Mass.



SUPERFICIAL TENSION.—A PAPER by M. Van der Mensbrugghe, explaining the action of the surface tension of liquids upon floating bodies, by a few simple experiments, and the action of oil upon waves. With 5 figures. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 662. Price 10 cents. To be had at this office and from all newsdealers.

Clark's Noiseless Rubber Truck Wheels  
Save floors. Anti-Friction Casters.  
Rubber Furniture Casters, etc.  
Catalogue free.  
Geo. P. Clark, Box L, Windsor Locks, Ct.

Proposals for Dredging in Penobscot River, Maine, between Bucksport and Winterport. UNITED STATES ENGINEER OFFICE. Portland, Maine, June 4, 1889.—Sealed proposals in triplicate for Dredging in Penobscot River, Maine, between Bucksport and Winterport, will be received at this office, No. 57 Congress Street, until 3 P. M. of Tuesday, July 2, 1889, and then opened. Attention is invited to Acts of Congress approved February 26, 1885, and February 23, 1887, Vol. 23, page 332, and Vol. 24, page 414, Statutes at Large. All necessary information furnished by JARED A. SMITH, Lieut.-Col. Corps of Engineers, U. S. Army.

To Vessel Owners.—ENGINEER OFFICE, U. S. ARMY, Newport, R. I., June 13, 1889. Vessels equipped for handling stone will soon be required for the Government work at the Harbor of Refuge at Block Island, R. I. Owners or parties interested who desire to charter such vessels to the United States, or to freight stone by the ton, are invited to communicate with this office.

Proposals for Cement.—U. S. ENGINEER OFFICE, 2136 Pennsylvania Avenue, N. W., Washington, D. C. June 8, 1889.—Sealed proposals, in triplicate, will be received at this office until 12 M. on Tuesday, June 25, 1889, for 1,500 barrels, more or less, of hydraulic Portland cement. Preference will be given to cement of domestic manufacture, conditions of quality and price being equal. For specifications and all information, apply to PETER C. HAINS, Lieut.-Col. of Engineers.

Sealed Bids will be received until July 1, 1889, for putting in Water Works in Wilmington, Ohio. Address ED. HUGHES, Corporation Clerk.

## Barnes' Patent Foot Power Machinery.

WORKERS OF WOOD OR METAL, without steam power, by using outfits of these Machines, can bid lower, and save more money from their jobs, than by any other means for doing their work. Also for

Industrial Schools or Home Training. With them boys can acquire practical journeymen's trades before they "go for themselves." Price-List Catalogue Free.  
W. F. & JOHN BARNES CO.,  
No. 1999—Baby St., Rockford, Ill.

## STEAM REGULATING SPECIALTIES

Made by us and guaranteed and used by all the car heating companies, railroad, etc.  
NASON REGULATOR CO., Boston, Mass.

## Shepard's New \$60 Screw-Cutting Foot Lathe

Foot and Power Lathes, Drill Presses, Scroll Saw Attachments, Chucks, Mandrels, Twist Drills, Dogs, Calipers, etc. Lathes on trial. Lathes on payment. Send for catalogue of Outfits for Amateurs or Artisans. Address H. L. SHEPARD, AGENT, 134 East 2d Street, Cincinnati, Ohio.

## USEFUL BOOKS.

Manufacturers, Agriculturists, Chemists, Engineers, Mechanics, Builders, men of leisure, and professional men, of all classes, need good books in the line of their respective callings. Our post office department permits the transmission of books through the mails at very small cost. A comprehensive catalogue of useful books by different authors, on more than fifty different subjects, has recently been published for free circulation at the office of this paper. Subjects classified with names of author. Persons desiring a copy, have only to ask for it, and it will be mailed to them. Address,

MUNN & CO., 361 Broadway, New York.

PULLEYS. Cheapest, Lightest, and Best. Made by Hardwood Split P. Co., Menasha, Wis.

WORKING MODELS & LIGHT MACHINERY. INVENTIONS DEVELOPED. Send for Model Circular. Jones Bros. E. Co., Cin'ti. O.

SEAMLESS TUBES.—DESCRIPTION of the various processes of manufacture; with 44 figures illustrative of the apparatus used. Contained in SCIENTIFIC AMERICAN SUPPLEMENT No. 638. Price 10 cents. To be had at this office and from all newsdealers.

CONTRACTORS MAKE THE LARGEST LINE OF ROAD GRADERS, SCRAPERS, PLOWING, AND RR CONSTRUCTION. THE WORLD'S LARGEST LINE OF WELLBORING TOOLS IN THE WORLD. MANUFACTURE THE LARGEST LINE OF WELLBORING TOOLS IN THE WORLD. CARPENTER ST., CARROLL AVE.—CHICAGO ILL. U.S.A.

## OIL WELL SUPPLY CO. Ltd.

91 & 92 WATER STREET, Pittsburgh, Pa.  
Manufacturers of everything needed for ARTESIAN WELLS for either Gas, Oil, Water, or Mineral Tests, Boilers, Engines, Pipe, Cordage, Drilling Tools, etc. Illustrated catalogue, price lists and discount sheets on request.

MARINE SIGNALS.—DESCRIPTION of various types of foghorns, sirens, buoys, lightships, and other forms of marine signals. With 25 figures. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 666. Price 10 cents. To be had at this office and from all newsdealers.

ARTESIAN Wells, Oil and Gas Wells, drilled by contract to any depth, from 50 to 300 feet. We also manufacture and furnish everything required to drill and complete same. Portable Horse Power and Mounted Steam Drilling Machines for 100 to 600 ft. Send 6 cents for illustrated catalogue. Pierce Artesian and Oil Well Supply Co., 80 Beaver Street, New York.

## PERFECT NEWSPAPER FILE

The Koch Patent File, for preserving newspapers, Magazines, and pamphlets, has been recently improved and price reduced. Subscribers to the SCIENTIFIC AMERICAN and SCIENTIFIC AMERICAN SUPPLEMENT can be supplied for the low price of \$1.50 by mail, or \$1.25 at the office of this paper. Heavy, board sides; inscription "SCIENTIFIC AMERICAN", in gilt. Necessary for every one who wishes to preserve the paper. Address MUNN & CO., Publishers SCIENTIFIC AMERICAN.

## ROCK BREAKERS AND ORE CRUSHERS

We manufacture and supply at short notice and lowest rates, Stone and Ore Crushers, containing the invention described in Letters Patent issued to Ed. W. Blake, June 23, 1886, to IMPROVEMENTS, for which Letters Patent were granted May 11th and July 20th, 1880, to Mr. S. L. Marsden. All Crushers supplied by us are constructed under the superintendence of Mr. Marsden, who, for the past twenty years, has been connected with the manufacture of Blake Crushers in this country and England. FARRER, FOUNDRY AND MACHINE CO., Manufacturers, ANSONIA, CONN. COPELAND & BACON, Agents, NEW YORK AND PHILADELPHIA.

## TO BUSINESS MEN.

The value of the SCIENTIFIC AMERICAN as an advertising medium cannot be overestimated. Its circulation is many times greater than that of any similar journal now published. It goes into all the States and Territories, and is read in all the principal libraries and reading rooms of the world. A business man wants something more than to see his advertisement in a printed newspaper. He wants circulation. This he has when he advertises in the SCIENTIFIC AMERICAN. And do not let the advertising agent influence you to substitute some other paper for the SCIENTIFIC AMERICAN, when selecting a list of publications in which you decide it is for your interest to advertise. This is frequently done, for the reason that the agent gets a larger commission from the papers having a small circulation than is allowed on the SCIENTIFIC AMERICAN. For rates see top of first column of this page, or address MUNN & CO., Publishers, 361 Broadway, New York.

## WATCHMAKERS

Send to American Watch Tool Co., Waltham, Mass., for price list of Whitcomb Lathes and for the new Webster-Whitcomb.

ELECTRICAL WELDING.—DESCRIPTION of a method of welding by electricity devised by Mr. N. Von Benardos, of St. Petersburg. With 38 illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 635. Price 10 cents. To be had at this office and from all newsdealers.

MODERN CAVALRY ON THE FIELD of Battle.—By Col. R. S. Liddell. An interesting historical resume of what has been accomplished by the cavalry in various notable battles, and discussing the value of this branch of the service. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 664. Price 10 cents. To be had at this office and from all newsdealers.

AGENTS \$75 per month and expenses paid any active man or woman to sell our goods by sample and live at home. Salary paid promptly and expenses in advance. Full particulars and sample case FREE. We mean just what we say. Address Standard Silverware Co., Boston, Mass.

IMPORTED PORTLAND CEMENT. "ELK," "LIONS HEAD," and "IMPERIAL." Strongest with mortar matrix in the United States. Safest for sidewalks, cellar, or concrete work. Eighteen years experience and knowledge for guidance. Remit 25 cents in postage stamps. S. L. MERCHANT CO., 15 State Street, New York City.

## CUTLER DESK BEST IN THE WORLD.

## The Paris Exposition--Illustrated.

The SCIENTIFIC AMERICAN SUPPLEMENT will for some months to come contain illustrations of the buildings and the most interesting objects to be seen at the great French Exposition opened at Paris a few days ago. The illustrations which will embellish the SCIENTIFIC AMERICAN SUPPLEMENT will add an interesting and useful feature to the publication, and subscribers to the regular edition of the SCIENTIFIC AMERICAN, who are not patrons of the SCIENTIFIC AMERICAN SUPPLEMENT, are advised to have their name enrolled on the SUPPLEMENT subscription list at once, so as to secure all the illustrated exposition numbers for preservation. Price, \$5 a year, \$2.50 for six months. News agents everywhere receive subscriptions, or remit to the publishers, MUNN & CO., 361 Broadway, New York.

## 2nd MACHINERY

N. Y. Mach'y Depot, Bridge Store 16, Frankfort St., N. Y.

LIME KILN that saves 36 per cent. over any patent kiln known. Guaranteed to burn No. 1 lime with coal, wood, or oil. Rights for sale. C. D. PAGE, Patentee, Rochester, N. Y.

INFLUENCE MACHINES.—A PAPER by James Wimshurst, giving a complete account of the recent forms of generators of static electricity. With 12 figures. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 647. Price 10 cents. To be had at this office and from all newsdealers.

FOR SALE. The Davis Siding-Gage Patents, Wm. F. HAYHURST, Investments and Loans, 923 17th Street, Denver, Colorado.

FAIR PRICE will be paid for a receipt to work up Cutting and Scrap Paper into some useful article. Address MITCHELL & BETTIS, Little Rock, Ark.

## The Scientific American

PUBLICATIONS FOR 1889.

The prices of the different publications in the United States, Canada, and Mexico are as follows:  
RATES BY MAIL.  
The Scientific American (weekly), one year \$3.00  
The Scientific American Supplement (weekly), one year 5.00  
The Scientific American, Export Edition (monthly) one year 5.00  
The Scientific American, Architects and Builders Edition (monthly), one year 2.50  
COMBINED RATES.  
The Scientific American and Supplement 7.00  
The Scientific American and Architects and Builders Edition 5.00  
The Scientific American, Supplement, and Architects and Builders Edition 9.00  
Proportionate Rates for Six Months.

This includes postage, which we pay. Remit by postal or express money order, or draft to order of MUNN & CO., 361 Broadway, New York.

CURE for the DEAF by FROST'S PAT. IMPROVED Cymonoid EAR DRUMS. Cymonoid EAR DRUMS. Whispers heard distinctly. Comfortable, invisible. Illustrated book with prospect, FREE. Address or call on F. HISCOX, 653 Broadway, N. Y. Name this paper.

## Advertisements.

Inside Page, each insertion --- 75 cents a line.  
Back Page, each insertion --- \$1.00 a line.

The above are charges per square line—about eight words per line. This notice shows the width of the line, and is set in square type. Engravings may be had at the same rate per square line, by measurement, as the letter press. Advertisements must be received at publication office as early as Thursday morning to appear in next issue.



## RIDE CYCLES!

VICTORS ARE BEST!

Bicycles, Tricycles, and Safeties.  
Send for free illustrated Catalogue.

Overman Wheel Co., Makers,  
BOSTON, MASS.

**THE COPYING PAD.—HOW TO MAKE**  
and how to use; with an engraving. Practical directions how to prepare the gelatine pad, and also the aniline ink by which the copies are made; how to apply the written letter to the pad; how to take off copies of the letter. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 438. Price 10 cents. For sale at this office and by all newsdealers in all parts of the country.

## THE KODAK CAMERA



Makes 100 instantaneous pictures by simply pressing a button. Anybody can use it who can wind a watch. No focusing. No tripod. Rapid Rectilinear Lens. Photographs moving objects. Can be used indoors.

Division of Labor—Operator can finish his own pictures, or send them to the factory to be finished. Morocco covered Camera, in hands some so-called leather case, loaded for 100 pictures.

For full description of "Kodak" see SCI. AM., Sept. 15, '88. Price, \$25.00. Reloading, \$2.00.

**The Eastman Dry Plate & Film Co.**  
Rochester, N. Y. 115 Oxford St., London.

Send for copy of Kodak Primer with Kodak Photograph.

**WAR SHIPS OF THE FUTURE.—AN**  
elaborate discussion of the features that are possibly to characterize the war ship of the future. With 8 figures. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 670. Price 10 cents. To be had at this office and from all newsdealers.




What is more aggravating than leaky valves, whether in House, Office, or Factory? If you wish to avoid annoyance, INSIST on having Jenkins Bros. Valves. Accept no valves as Jenkins Bros. unless stamped with our "Trade Mark" like cut.

## JENKINS BROS.

71 John Street, New York.  
105 Milk Street, Boston.  
21 North 5th Street, Phila.  
54 Dearborn Street, Chicago.

**ELECTRO MOTOR, SIMPLE, HOW TO**  
make. By G. M. Hopkins.—Description of a small electro motor devised and constructed with a view to assisting amateurs to make a motor which might be driven with advantage by a current derived from a battery, and which would have sufficient power to operate a foot lathe or any machine requiring not over one man power. With 11 figures. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 641. Price 10 cents. To be had at this office and from all newsdealers.

## AMERICAN POP SAFETY VALVE.



The only Automatic Adjusting Safety Valve ever produced. For Locomotive, Stationary, Marine, and Portable Boilers. It does not infringe on any other valve made. We guarantee all parties buying or using them protection against all suits. Accepted for application to all marine boilers, by the Board of Supervisors, Inspectors of Steam Vessels, and approved by the Secretary of the Treasury at Washington, D. C., 1885. Approved and its adoption recommended on U. S. Naval Steamships, April 15, 1885, by U. S. Naval Board of Examiners.

**AMERICAN STEAM GAUGE COMPANY,**  
34 Chardon Street, Boston, Mass.

**GRAPHOPHONE AND PHONOGRAPH.**  
—An interesting account of the Edison, Bell, and Taintor apparatus for the mechanical reproduction of speech, with detailed description of the same. With 11 figures. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 669. Price 10 cents. To be had at this office and from all newsdealers.

## Scientific Book Catalogue

RECENTLY PUBLISHED.

Our new catalogue containing over 100 pages, including works on more than fifty different subjects. Will be mailed free to any address on application.

MUNN & CO., Publishers Scientific American,  
361 Broadway, New York.

**TOOL AGENTS WANTED.**  
In every shop in the United States.  
THE FINEST OF MECHANICAL TOOLS A SPECIALTY.  
C. H. JAMES, 35 LAKE ST. CHICAGO, ILL.

## PATENTS.

MESSRS. MUNN & CO., in connection with the publication of the SCIENTIFIC AMERICAN, continue to examine improvements, and to act as Solicitors of Patents for inventors.

In this line of business they have had forty-two years' experience, and now have unequalled facilities for the preparation of Patent Drawings, Specifications, and the prosecution of Applications for Patents in the United States, Canada, and Foreign Countries. Messrs. Munn & Co. also attend to the preparation of Caveats, Copyrights for Books, Labels, Reissues, Assignments, and Reports on Infringements of Patents. All business entrusted to them is done with special care and promptness, on very reasonable terms.

A pamphlet sent free of charge, on application, containing full information about Patents and how to procure them; directions concerning Letters, Copyrights, Designs, Patents, Appeals, Reissues, Infringements, Assignments, Rejected Cases. Hints on the Sale of Patents, etc.


We also send, free of charge, a Synopsis of Foreign Patent Laws, showing the cost and method of securing patents in all the principal countries of the world.

MUNN & CO., Solicitors of Patents,  
361 Broadway, New York.  
BRANCH OFFICES.—No. 622 and 624 F Street, Pacific Building, near 7th Street, Washington, D. C.

## ASBESTOS

MADE ENTIRELY OF ASBESTOS.  
**Absolutely Fire Proof.**  
BRAIDED PACKING, MILL BOARD, SHEATHING, CEMENT, FIBRE AND SPECIALTIES.  
CHALMERS-SPENCE CO., FOOT E. 8TH ST., N. Y.  
BRANCHES: Phila, 24 Strawberry St. Chicago, 86 E. Lake St. Pittsburg, 414 Lewis Block.

**JAMES B. EADS.—AN ACCOUNT OF**  
the life and labors of this eminent engineer. With a portrait. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 592. Price 10 cents. To be had at this office and from all newsdealers.



INVENTORS and others desiring new articles manufactured and introduced, address P. O. Box 86, Cleveland, O.



**PETROLEUM BOAT. DESCRIPTION**  
of a petroleum motor devised by Mr. Lenoir for the propulsion of small boats. With 2 figures. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 637. Price 10 cents. To be had at this office and from all newsdealers.

## PIPE COVERINGS

Made entirely of ASBESTOS.

**Absolutely Fire Proof.**

**THE ARMSTRONG MFG. CO.**  
BRIDGEPORT, CONN.  
WATER, GAS AND STEAM FITTERS' TOOLS.



Stocks and Dies for Pipe, Bolts, and Brass Pipe, Wrenches, Pipe Vises, Pipe Cutters, etc.) Catalogues sent free on application.

## THE ONLY PRACTICAL Low-Priced Typewriter

First-Class, Rapid, Durable, Business  
**WORLD TYPEWRITER, 44 characters, \$10; 77 characters, \$15.**

Catalogue free. Typewriter Dept., POPE MFG. CO., Boston, New York, Chicago.



**THE EIFFEL TOWER.—AN EXCEL-**  
lent engraving of the Eiffel one thousand-feet-high tower, which was opened to the public a few days ago, and which is to form a part of the French Exposition attractions, may be found, with description, in the SCIENTIFIC AMERICAN SUPPLEMENT, No. 554. To be had from newsdealers or at this office. Price 10 cents.

**THE CUSHMAN KEY DRILL CHUCK.**  
This is an improvement over all other chucks of its class and is fully guaranteed.  
DIAM. TOOLS PRICE  
No. 1, 2 in. 0 to 1/4 in. \$6.50  
No. 2, 2 1/4 in. 1/4 to 1/2 in. 8.00  
Sold by the trade and Manufactured by THE CUSHMAN CHUCK CO., Hartford, Conn.

## VULCABESTON

## FOR ELECTRICAL PURPOSES.

Switch Boards, Armature Sleeves, Insulating Washers, Insulating Parts for Arc Lights, Insulating Parts for Incandescent Lights, Battery Cells, Insulating Parts for Motors, Insulating Parts for Chandeliers, Insulating Parts for Dynamos.

Special styles and shapes to order.

Prices on application.

## H. W. Johns Manufacturing Co.

SOLE MANUFACTURERS OF

H. W. Johns' Asbestos Millboard, Sheathings, Building Felts, Fire-Proof Paints, Liquid Paints, Asbestos Roofing, etc.

87 Malden Lane, New York.

CHICAGO. PHILADELPHIA. LONDON.

## THE BOOKWALTER STEEL AND IRON CO.

Is now prepared to grant licenses under the Bookwalter, Robert, and other patents owned by it. Parties desiring licenses to operate under these patents will please state, in their application, for what purpose they design using the process, whether for steel castings, for ingots of dead soft steel, for tool steel, or for ordnance purposes.

**No. 18 Cortlandt Street, New York.**

## PENBERTHY IMPROVED AUTOMATIC INJECTOR.

Why 20,000 have been sold in two years. Because they cost less than others and do equal work. Lift 20 feet and work from head as well. Re-start themselves and require no watching. Will lift through hot pipes, work from 25 to 150 lbs. pressure. Parts removable without disconnecting, also interchangeable. Send for pamphlet Penberthy Injector Co., Detroit, Mich.

## THE AMERICAN BELL TELEPHONE CO.

95 MILK ST., BOSTON, MASS.

This Company owns the Letters Patent granted to Alexander Graham Bell, March 7th, 1876, No. 174,465, and January 30th, 1877, No. 186,787.

The transmission of Speech by all known forms of Electric Speaking Telephones infringes the right secured to this Company by the above patents, and renders each individual user of telephones not furnished by it or its licensees responsible for such unlawful use, and all the consequences thereof, and liable to suit therefor.



**BIBB'S Celebrated Original BALTIMORE FIRE-PLACE HEATERS**  
To warm upper and lower rooms The Handsomest and Most Economical Coal Stoves in the world.  
B. C. BIBB & SON  
Stove Foundry, Baltimore, Md.  
HARLEIZED PLATE PATENT  
New and Beautiful Designs.



**WORKING MODELS** and Experimental or wood, made to order by MASON & RAUCH, successors to J. F. Werner, 62 Centre Street, New York.

## OTTO GAS ENGINES.

Over 25,000 Sold.  
Horizontal ..... Otto ..... Gas Engines.  
Vertical ..... Otto ..... Gas Engines.  
Twirl Cylinder ..... Otto ..... Gas Engines.  
Combined ..... Otto ..... Gas Engines and Pumps.  
Combined ..... Otto ..... Gas Engines and Dynamos.

**OTTO GAS ENGINE WORKS,**  
CHICAGO, PHILADELPHIA.

New York Agency,  
18 Vesey Street.

**YELLOWSTONE PARK.—AN IN-**  
teresting description of this region of wonders, with its hot springs, geysers, caves, lakes, etc. With 11 illustrations. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 663. Price 10 cents. To be had at this office and from all newsdealers.

## VAN DUZEN GAS ENGINE

NO BOILER. NO COAL. NO ENGINEER.

No Extra WATER RENT or INSURANCE.

INSTANTLY STARTED.

DURABLE, RELIABLE, SAFE and ECONOMICAL.

Send for description and prices.

Van Duzen Gas Engine Co.,  
68 E. 2nd St., CINCINNATI, O.

## STANDARD TOOL CO.

ATHOL, MASS.

MANUFACTURERS OF

The Celebrated Chapin Try and Center Square, Standard Steel Rules, Steel Caliper Rules, Universal Bevels, Caliper Gauges, Improved Surface Gauges, Bevel Protractors, Depth Gauges, Screw Pitch and Center Gauges, Hardened Steel Squares, Graduated Steel Squares, Spring Calipers, Pliers, Straight Edges, etc., etc.

WRITE FOR ILLUSTRATED CATALOGUE AND PRICE LIST OF FULL LINE

## SYRACUSE MALLEABLE IRON WORKS

**THE PHONOGRAPH.—A DETAILED**  
description of the new and improved form of the phonograph just brought out by Edison. With 8 engravings. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 632. Price 10 cents. To be had at this office and from all newsdealers.

PATENT

## JACKET KETTLES,

Plain or Porcelain Lined. Tested to 100 lb. pressure. Send for Lists.  
HAND, BURR & CO.  
614 and 616 Market St., Philadelphia, Pa.

**NOTES ON TECHNICAL EDUCATION.**—A paper by Dr. R. H. Thurston, in which the author discusses the reason and purpose of technical education, and its value in the development of the powers of the masses of the people, and the securing of the greatest possible prosperity of the nation. Contained in SCIENTIFIC AMERICAN SUPPLEMENT, No. 668. Price 10 cents. To be had at this office and from all newsdealers.

## Novelty HOT AIR Furnaces

Expose an Immense Heated Surface.

Extract all the Heat from the Gases. Furnish Pure Warm Air in abundance. Fifteen Years of Test. Universally Satisfactory.

Send for "Our Furnace Book."

**Abram Cox Stove Co.**

MANUFACTURERS,  
Philadelphia and New York.

**KEY SEATING** Machines and 20" Drills.  
W. P. DAVIS, Rochester, N. Y.

## THE Scientific American

ESTABLISHED 1846.

The Most Popular Scientific Paper in the World.

Only \$3.00 a Year, including Postage. Weekly.  
52 Numbers a Year.

This widely circulated and splendidly illustrated paper is published weekly. Every number contains sixteen pages of useful information and a large number of original engravings of new inventions and discoveries, representing Engineering Works, Steam Machinery, New Inventions, Novelties in Mechanics, Manufactures, Chemistry, Electricity, Telegraphy, Photography, Architecture, Agriculture, Horticulture, Natural History, etc. Complete List of Patents each week.

**Terms of Subscription.**—One copy of the SCIENTIFIC AMERICAN will be sent for one year—52 numbers—postage prepaid, to any subscriber in the United States or Canada, on receipt of three dollars by the publishers; six months, \$1.50; three months, \$1.00.

**Clubs.**—Special rates for several names, and to Post Masters. Write for particulars.

The safest way to remit is by Postal Order, Draft, or Express Money Order. Money carefully placed inside of envelopes, securely sealed, and correctly addressed, seldom goes astray, but is at the sender's risk. Address all letters and make all orders, drafts, etc., payable to

MUNN & CO.,  
361 Broadway, New York.

## THE Scientific American Supplement.

This is a separate and distinct publication from THE SCIENTIFIC AMERICAN, but is uniform therewith in size, every number containing sixteen large pages full of engravings, many of which are taken from foreign papers, and accompanied with translated descriptions. THE SCIENTIFIC AMERICAN SUPPLEMENT is published weekly, and includes a very wide range of contents. It presents the most recent papers by eminent writers in all the principal departments of Science and the Useful Arts, embracing Biology, Geology, Mineralogy, Natural History, Geography, Archaeology, Astronomy, Chemistry, Electricity, Light, Heat, Mechanical Engineering, Steam and Railway Engineering, Mining, Ship Building, Marine Engineering, Photography, Technology, Manufacturing Industries, Sanitary Engineering, Agriculture, Horticulture, Domestic Economy, Biography, Medicine, etc. A vast amount of fresh and valuable information obtainable in no other publication.

The most important Engineering Works, Mechanisms, and Manufactures at home and abroad are illustrated and described in the SUPPLEMENT.

Price for the SUPPLEMENT for the United States and Canada, \$5.00 a year, or one copy of the SCIENTIFIC AMERICAN and one copy of the SUPPLEMENT, both mailed for one year for \$7.00. Single copies 10 cents. Address and remit by postal order, express money order, or check.

MUNN & CO., 361 Broadway, N. Y.  
Publishers SCIENTIFIC AMERICAN.

## Building Edition.

THE SCIENTIFIC AMERICAN ARCHITECTS' AND BUILDERS' EDITION is issued monthly. \$2.50 a year. Single copies, 25 cents. Forty large quarto pages, equal to about two hundred ordinary book pages; forming a large and splendid Magazine of Architecture, richly adorned with elegant plates in colors, and with other fine engravings; illustrating the most interesting examples of modern Architectural Construction and allied subjects.

A special feature is the presentation in each number of a variety of the latest and best plans for private residences, city and country, including those of very moderate cost as well as the more expensive. Drawings in perspective and in color are given, together with full Plans, Specifications, Sheets of Details, Estimates, etc.

The elegance and cheapness of this magnificent work have won for it the Largest Circulation of any Architectural publication in the world. Sold by all newsdealers. \$2.50 a year. Remit to

MUNN & CO., Publishers,  
361 Broadway, New York.

## PRINTING INKS.

THE "Scientific American" is printed with CHAS. KNEU JOHNSON & CO.'S INK. Tenth and Lombard Sts., Phila., and 47 Rose St., opp. Duane St., N. Y.